

PIKE 1078 update FW S.O.P

1. Please prepare the USB flash that can boot into DOS.
2. Unzip attached file to a bootable USB drive.
3. Plug PIKE card & iButton & USB drive on your system and power on.
(Pls remember to remove other PCI or PCIE add-on cards.)
4. Boot into DOS mode.
5. Use command "FW" to upgrade it.

```
C:\1078>fw
```


6. Update OK!!

```
C:\1078>megacli -adpflash -f 1078.rom -noverchk -a0
DOS/4GW Protected Mode Run-time Version 1.97
Copyright (c) Rational Systems, Inc. 1990-1994

Adapter 0: MegaRAID SAS PCI Express(TM) ROMB
Vendor ID: 0x1000, Device ID: 0x0060

Flashing image to adapter...
Flash Completed.
```

7. Reboot system
8. You can double confirm the FW Package Version (ex: 11.0.1-0022) in WebBIOS -> Controller Properties.



MegaRAID BIOS Config Utility Controller Information



MegaRAID SAS PCI Express(TM) ROMB

Serial Number	None	FRU	None
SubVendorID	0x1043	Encryption Capable	No
SubDeviceID	0x824d	NVRAMSize	32 KB
PortCount	8	Memory Size	256 MB
HostInterface	PCIE	Min Stripe Size	8 KB
Firmware Version	1.40.92-0746	Max Stripe Size	1 MB
FW Package Version	11.0.1-0022	Virtual Drive Count	0
Firmware Time	Nov 3 2009:12:10:24	Drive Count	0
WebBIOS Version	2.2-19-Rel		

[Next](#)[Home](#)[Back](#)