

P7H55-M LX/USB3

DDR3 1067 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	Socket support (O)	
								1 DIMM	2 DIMM
Crucial	CT12864BA1067.8FF	1GB	SS	Micron	9GF22D9KPT	7	-	●	●
Crucial	CT25664BA1067.16FF	2GB	DS	Micron	9HF22D9KPT	7	-	●	●
ELPIDA	EBJ10UE8EDF0-AE-F	1GB	SS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●
ELPIDA	EBJ21UE8EDF0-AE-F	2GB	DS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●
KINGSTON	KVR1066D3N7/1G	1GB	SS	KTC	D1288JPNDPLD9U	7	1.5V	●	●
KINGSTON	KVR1066D3N7/2G	2GB	DS	ELPIDA	J1108BDSE-DJ-F	7	1.5V	●	●
KINGSTON	KVR1066D3N7/4G	4GB	DS	Hynix	H5TQ2G83AFR	7	1.5V	●	●
Micron	MT8JTF12864AZ-1G1F1	1GB	SS	Micron	9GF22D9KPT	7	-	●	●
Micron	MT16JTF25664AZ-1G1F1	2GB	DS	Micron	9HF22D9KPT	7	-	●	●
OCZ	OCZ3G1066LV4GK	4GB (2 x 2GB)	DS	Micron	9BF27D9KPV	7-7-7-20	1.65V	●	●
SAMSUNG	M378B2873EH1-CF8	1GB	SS	Samsung	SEC 901 HCF8 K4B1G0846E	-	-	●	●
SAMSUNG	M378B5273BH1-CF8	4GB	DS	SAMSUNG	846 K4B2G0846B-HCF8	-	-	●	●
Vendor	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.		

4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports 2 modules inserted into both the blue or black slots as two pairs of Dual-channel memory configuration

When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended. It is recommended to install the memory modules from the slots for better overclocking capability.

The default DIMM frequency depends on its Serial Presence Detect (SPD), which is The standard way of accessing information from a memory module. Under The default state, some memory modules for overclocking may operate at a lower frequency than The vendor-marked value.

P7H55-M LX/USB3

DDR3 1333 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	Socket support (O)	
								1 DIMM	2 DIMM
A-Data	AD31333G002GMU	2GB	DS	-	-	8-8-8-24	1.65-1.85V	●	●
Apacer	78.A1GC6.9L1	2GB	DS	APACER	AM5D5808DEWSBG	-	-	●	●
CORSAIR	CM3X1024-1333C9	1GB	SS	-	-	9-9-9-24	1.60V	●	●
CORSAIR	TR3X3G1333C9	1GB 2GB(3x 1GB)	SS	-	-	9-9-9-24	1.50V	●	●
Crucial	CT12864BA1339.8FF	1GB	SS	Micron	9FF22D9KPT	9	-	●	●
Crucial	BL25664BN1337.16FF (XMP)	8GB(2x 4GB)	DS	-	-	7-7-7-24	1.65V	●	●
ELPIDA	EJB10UE8EDF0-DJ-F	1GB	SS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●
G.SKILL	F3-10600CL8D-2GBHK(XMP)	1GB	SS	G.SKILL	-	-	-	●	●
G.SKILL	F3-10600CL9D-2GBNQ	1GB	DS	G.SKILL	-	-	-	●	●
G.SKILL	F3-10600CL8D-4GBHK(XMP)	4GB(2x 2GB)	DS	-	-	8-8-8-21	1.5-1.6V	●	●
G.SKILL	F3-10666CL7D-8GBRH(XMP)	8GB(2x 4GB)	DS	-	-	7-7-7-21	1.5V	●	●
GEIL	GG34GB1333C9DC	4GB(2x 2GB)	DS	GEIL	GL1L128M88BA12N	9-9-9-24	1.3V(low voltage)	●	●
GEIL	GV34GB1333C9DC	4GB(2x 2GB)	DS	-	-	9-9-9-24	1.5V	●	●
Hynix	HMT112U6TFR8A-H9	1GB	SS	HYNIX	H5TC1G83TFRH9A	-	1.35V(low voltage)	●	●
KINGMAX	FLFE85F-B8KL9	2GB	DS	KINGMAX	KKB8FNWBFGNX-26A	-	-	●	●
KINGMAX	FLFF65F-C8KM9-NEES	4GB	DS	KINGMAX	KFC8FNMXF-BXX-15A	-	-	●	●
Kingston	KVR1333D3N9/2G	2GB	DS	ELPIDA	J1108BDSE-DJ-F	9	1.5V	●	●
Kingston	KHX1333C9D3UK2/4GX(XMP)	4GB(2x 2GB)	DS	-	-	9	XMP 1.25V	●	●
Micron	MT8JTF12864AZ-1G4F1	1GB	SS	Micron	9FF22D9KPT	9	-	●	●
OCZ	OCZ3F13334GK	4GB(2x 2GB)	DS	-	-	9-9-9-20	1.7V	●	●
OCZ	OCZ3G1333LV6GK	8GB(2x 4GB)	DS	-	-	9-9-9-20	1.65V	●	●
PSC	AL8F8G73D-DG1	2GB	DS	PSC	A3P1GF3DGF928M9B05	8-8-8-24	1.5V	●	●
SAMSUNG	M378B2873FHS-CH9	1GB	SS	SAMSUNG	K4B1G0846F	-	-	●	●
SAMSUNG	M378B5673FH0-CH9	2GB	DS	SAMSUNG	K4B1G0846F	-	-	●	●
Super Talent	W1333UX6GM	6GB(3x 2GB)	DS	Micron	0BF27D9KPT	9-9-9-24	1.5V	●	●
Vendor	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.		

4 DIMM Slots

- 1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- 2 DIMM:** Supports 2 modules inserted into both the blue or black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.