

## V\_P8H61E

### DDR3 1067 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand
<b>Crucial</b>	CT12864BA1067.8FF	1GB	SS	Micron
<b>Crucial</b>	CT25664BA1067.16FF	2GB	DS	Micron
<b>ELPIDA</b>	EBJ10UE8EDF0-AE-F	1GB	SS	ELPIDA
<b>ELPIDA</b>	EBJ11UD8BAFA-AE-E	1GB	DS	Elpida
<b>ELPIDA</b>	EBJ21UE8EDF0-AE-F	2GB	DS	ELPIDA
<b>KINGSTON</b>	KVR1066D3N7/1G	1GB	SS	KTC
<b>KINGSTON</b>	KVR1066D3N7/2G	2GB	DS	ELPIDA
<b>KINGSTON</b>	KVR1066D3N7/4G	4GB	DS	Hynix
<b>Micron</b>	MT8JTF12864AZ-1G1F1	1GB	SS	Micron
<b>Micron</b>	MT16JTF25664AZ-1G1F1	2GB	DS	Micron
<b>OCZ</b>	OCZ3G1066LV4GK	4GB(2 x	DS	Micron
<b>Elixir</b>	M2Y2G64CB8HC5N-BE	2GB	DS	Elixir
<b>Elixir</b>	M2Y2G64CBHA9N-BE	2GB	DS	-
<b>Elixir</b>	M2Y2G64CBHC9N-BE	2GB	DS	Elixir
<b>Kingtiger</b>	2GB DIMM PC3-8500	2GB	DS	Hynix

#### 4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-chan
- **2 DIMM:** Supports one pair of modules inserted into either the [blu](#)
- **4 DIMM:** Supports 4 modules inserted into both the [blue](#) and [blac](#)

-When installing total memory of 4GB capacity or more, Windows 32-bit operation sy

-It is recommended to install the memory modules from the slots for better overclock

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is

Chip NO.	Timing	Voltage	DIMM socket support (Optional)		
			1 DIMM	2 DIMM	4 DIMM
9GF22D9KPT	7	-	•		•
9HF22D9KPT	7	-	•	•	
J1108EDSE-DJ-F	-	1.35V(low voltage)	•		•
J5308BASE-AC-E	-	-	•	•	
J1108EDSE-DJ-F	-	1.35V(low voltage)	•		
D1288JPNDPLD9U	7	1.5V	•		•
J1108BDSE-DJ-F	7	1.5V	•		
H5TQ2G83AFR	7	1.5V	•		
9GF22D9KPT	7	-	•		•
9HF22D9KPT	7	-	•	•	
9BF27D9KPV	7-7-7-20	1.65V	•	•	
N2CB1G80CN-BE	-	-	•	•	
-	7-7-7-20	-	•	•	
-	-	-	•		
H5TQ1G83AFP G7C	-	-	•	•	

nel memory configuration

ie slots or the **black** slots as one pair of Dual-channel memory configuration  
**k** slots as two pairs of Dual-channel memory configuration

stem may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is r  
ing capability.

the standard way of accessing information from a memory module. Under the default state, sc

ecommended.

ome memory modules for overclocking may operate at a lower frequency than the vendor-m.

arked value.