


Step1: Make sure the AC adapter is connected to system.


Step2: Download the file (1008HA.ZIP) and unzipped it directly



Step3: Double-click the downloaded file (1008HA.EXE) and press "YES" to reboot system.



Step4: Kindly keep the power supply on and not modify or execute any program while performing BIOS update.



Step5: BIOS update finished, please press power button to shut down & restart the system.

```
Boot Block Compatible Version Ver.017
Please do NOT insert any disc into CD-ROM or Floppy
if you want to recovery with an USB device.
EZ-Flash starting BIOS update.....
DO KEEP the power supply on and NOT touch the system
update.
Reading file "1008HA.ROM"
Start Erasing...\
Start Programming.../
Start Erasing EC Firmware...
Start Programming EC Firmware...
The BIOS update is finished.
Please press power button to shut down the system._
```

Step6: Double check the BIOS revision named as "0402" and press "F2" to access to Windows platform.

```
American Megatrends
www.ami.com
ASUS 1008HA ACPI BIOS Revision 0402
CPU : Intel(R) Atom(TM) CPU N260  @ 1.66GHz
Speed : 1.66 GHz

Press ESC for BBS POPUP
Press F9 for System Recovery
DDRII-533/CL4, Single-Channel Mode
Initializing USB Controllers .. Done.
1016MB OK (Installed Memory Size:1024MB)

Auto-Detecting Pri Master..IDE Hard Disk
Pri Master: ST9160310AS 0303
Ultra DMA Mode-5, S.M.A.R.T. Capable and Stat
Auto-detecting USB Mass Storage Devices ..
00 USB mass storage devices found and configured.

Please enter setup to recover BIOS setting
Press F1 to Run SETUP
Press F2 to load default values and continue
```

Step7: Finished BIOS Update & Enjoy your upgraded Wi-Fi performance.

