

## P8Q67-M DO

### DDR3 1067 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	MM socket support (Optional)		
								1 DIMM	2 DIMM	4 DIMM
Crucial	CT12864BA1067.8FF	1GB	SS	Micron	9GF22D9KPT	7	-	●	●	●
Crucial	CT25664BA1067.16FF	2GB	DS	Micron	9HF22D9KPT	7	-	●	●	●
ELPIDA	EJB10UE8EDF0-AE-F	1GB	SS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●	●
ELPIDA	EJB11UD8BAFA-AE-E	1GB	DS	Elpida	J5308BASE-AC-E	-	-	●	●	●
ELPIDA	EJB21UE8EDF0-AE-F	2GB	DS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●	●
KINGSTON	KVR1066D3N7/1G	1GB	SS	KTC	D1288JPNDPLD9U	7	1.5V	●	●	●
KINGSTON	KVR1066D3N7/2G	2GB	DS	ELPIDA	J1108BDSE-DJ-F	7	1.5V	●	●	●
KINGSTON	KVR1066D3N7/4G	4GB	DS	Hynix	H5TQ2G83AFR	7	1.5V	●	●	●
Micron	MT8JTF12864AZ-1G1F1	1GB	SS	Micron	9GF22D9KPT	7	-	●	●	●
Micron	MT16JTF25664AZ-1G1F1	2GB	DS	Micron	9HF22D9KPT	7	-	●	●	●
OCZ	OCZ3G1066LV4GK	4GB(2 x 2GB)	DS	Micron	9BF27D9KPV	7-7-7-20	1.65V	●	●	●
SAMSUNG	M378B2873EH1-CF8	1GB	SS	Samsung	SEC 901 HCF8 K4B1G0846E	-	-	●	●	●
SAMSUNG	M378B5273BH1-CF8	4GB	DS	SAMSUNG	846 K4B2G0846B-HCF8	-	-	●	●	
Elixir	M2Y2G64CB8HC5N-BE	2GB	DS	Elixir	N2CB1G80CN-BE	-	-	●	●	●
Elixir	M2Y2G64CBHA9N-BE	2GB	DS	-	-	7-7-7-20	-	●	●	●
Elixir	M2Y2G64CBHC9N-BE	2GB	DS	Elixir	-	-	-			
Kingtiger	2GB DIMM PC3-8500	2GB	DS	Hynix	H5TQ1G83AFP G7C	-	-	●	●	●

#### 4 DIMM Slots

- 1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- 2 DIMM:** Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
- 4 DIMM:** Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

## P8Q67-M DO

### DDR3 1333 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	MM socket support (Optional)		
								1 DIMM	2 DIMM	4 DIMM
A-Data	AD31333001GOU	1GB	SS	A-Data	AD30908C8D-151C E0906	-	-	●	●	●
A-Data	AD31333G001GOU	3GB(3 x 1GB)	SS	-	-	8-8-8-24	1.65-1.85V	●	●	
A-Data	AD31333002GOU	2GB	DS	A-Data	AD30908C8D-151C E0903	-	-	●	●	●
A-Data	AD31333G002GMU	2GB	DS	-	-	8-8-8-24	1.65-1.85V	●	●	●
Apacer	78.A1GC6.9L1	2GB	DS	APACER	AM5D5808DEWSBG	-	-	●	●	●
Apacer	78.A1GC6.9L1	2GB	DS	Apacer	AM5D5808FEQSBG	9	-	●	●	●
CORSAIR	CM3X1024-1333C9DHX	1GB	SS	-	-	9-9-9-24	1.60V	●	●	
CORSAIR	CM3X1024-1333C9	1GB	SS	-	-	9-9-9-24	1.60V	●	●	●
CORSAIR	TR3X3G1333C9 G	3GB(3 x 1GB)	SS	-	-	9-9-9-24	1.50V	●	●	
CORSAIR	TR3X3G1333C9 G	3GB(3 x 1GB)	SS	-	-	9-9-9-24	1.50V	●	●	
CORSAIR	TR3X3G1333C9	3GB(3 x 1GB)	SS	-	-	9-9-9-24	1.50V	●	●	●
CORSAIR	CM3X1024-1333C9DHX	1GB	DS	Corsair	-	-	-			
CORSAIR	CMD24GX3M6A1333C9(XMP)	24GB(6x4GB)	DS	-	-	9-9-9-24	1.60V	●	●	●
CORSAIR	CM3X2048-1333C9DHX	2GB	DS	-	-	-	-	●	●	
CORSAIR	TW3X4G1333C9 G	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.50V	●	●	●
CORSAIR	CMX8GX3M4A1333C9	8GB(4 x 2GB)	DS	-	-	9-9-9-24	1.50V	●	●	●
Crucial	CT12864BA1339.8FF	1GB	SS	Micron	9FF22D9KPT	9	-	●	●	●
Crucial	CT25664BA1339.16FF	2GB	DS	Micron	9KF27D9KPT	9	-	●	●	●
Crucial	BL25664BN1337.16FF (XMP)	6GB(3 x 2GB)	DS	-	-	7-7-7-24	1.65V	●	●	●
ELPIDA	EJB10UE8EDF0-DJ-F	1GB	SS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●	●
ELPIDA	EJB21UE8EDF0-DJ-F	2GB	DS	ELPIDA	J1108EDSE-DJ-F	-	1.35V(low voltage)	●	●	
G.SKILL	F3-10600CL8D-2GBHK(XMP)	1GB	SS	G.SKILL	-	-	-	●	●	●
G.SKILL	F3-10666CL7T-3GBPK(XMP)	3GB(3 x 1GB)	SS	-	-	7-7-7-18	1.5~1.6V	●	●	●
G.SKILL	F3-10666CL9T-3GBNQ	3GB(3 x 1GB)	SS	-	-	9-9-9-24	1.5~1.6V	●	●	
G.SKILL	F3-10600CL9D-2GBNQ	1GB	DS	G.SKILL	-	-	-			
G.SKILL	F3-10600CL8D-4GBHK(XMP)	4GB(2 x 2GB)	DS	-	-	8-8-8-21	1.5~1.6V	●	●	
G.SKILL	F3-10666CL8D-4GBECO(XMP)	4GB(2 x 2GB)	DS	-	-	8-8-8-24	XMP 1.35V	●	●	
G.SKILL	F3-10666CL7T-6GBPK(XMP)	6GB(3 x 2GB)	DS	-	-	7-7-7-18	1.5~1.6V	●	●	●
G.SKILL	F3-10666CL7D-8GBRH(XMP)	8GB(2 x 4GB)	DS	-	-	7-7-7-21	1.5V	●	●	●
G.SKILL	F3-10666CL9D-8GBRL	8GB(2 x 4GB)	DS	-	-	9-9-9-24	1.5V			
GEIL	GET316GB1333C9QC	16GB ( 4x 4GB )	DS	-	-	9-9-9-24	1.5V	●	●	
GEIL	GV32GB1333C9DC	2GB(2 x 1GB)	DS	-	-	9-9-9-24	1.5V	●	●	●
GEIL	GV34GB1333C7DC	2GB	DS	-	-	7-7-7-24	1.5V	●	●	
GEIL	GG34GB1333C9DC	4GB(2 x 2GB)	DS	GEIL	GL1L128M88BA12N	9-9-9-24	1.3V(low voltage)	●	●	
GEIL	GV34GB1333C9DC	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.5V	●	●	●
Hynix	HMT112U6TFR8A-H9	1GB	SS	HYNIX	H5TC1G83TFRH9A	-	1.35V(low voltage)	●	●	●
Hynix	HMT125U6TFR8A-H9	2GB	DS	HYNIX	H5TC1G83TFRH9A	-	1.35V(low voltage)	●	●	●

<b>KINGMAX</b>	FLFD45F-B8KL9	1GB	SS	KINGMAX	KKB8FNWBFGNX-27A	-	-	●	●	●
<b>KINGMAX</b>	FLFE85F-C8KM9-NAES	2GB	SS	KINGMAX	KFC8FNMXF-BXX-15A	-	-	●	●	●
<b>KINGMAX</b>	FLFE85F-B8KL9	2GB	DS	KINGMAX	KKB8FNWBFGNX-26A	-	-	●	●	●
<b>KINGMAX</b>	FLFF65F-C8KM9-NEES	4GB	DS	KINGMAX	KFC8FNMXF-BXX-15A	-	-	●	●	●
<b>Kingston</b>	KVR1333D3N9/1G	1GB	SS	ELPIDA	J1108BDBG-DJ-F	9	1.5V	●	●	●
<b>KINGSTON</b>	KVR1333D3N9/2G(矮版)	2GB	DS	ELPIDA	J1108BDBG-DJ-F	9	1.5V	●	●	●
<b>Kingston</b>	KVR1333D3N9/2G	2GB	DS	KTC	D1288JPNDPLD9U	9	1.5V	●	●	●
<b>Kingston</b>	KVR1333D3N9/2G	2GB	DS	ELPIDA	J1108BDSE-DJ-F	9	1.5V	●	●	●
<b>Kingston</b>	KHX1333C7D3K2/4GX(XMP)	4GB(2 x 2GB)	DS	-	-	7	1.65V	●	●	●
<b>Kingston</b>	KHX1333C9D3UK2/4GX(XMP)	4GB(2 x 2GB)	DS	-	-	9	XMP 1.25V	●	●	●
<b>KINGSTON</b>	KVR1333D3N9/4G(矮版)	4GB	DS	HYNIX	H5TQ2G83AFRH9C	9	1.5V	●	●	●
<b>KINGSTON</b>	KVR1333D3N9/4G	4GB	DS	Hynix	H5TQ2G83AFR	-	-	●	●	●
<b>MICRON</b>	MT4JTF12864AZ-1G4D1	1GB	SS	MICRON	D9LGQ	-	-	●	●	●
<b>Micron</b>	MT8JTF12864AZ-1G4F1	1GB	SS	Micron	9FF22D9KPT	9	-	●	●	●
<b>MICRON</b>	MT8JTF25664AZ-1G4D1	2GB	SS	MICRON	D9LGK	-	-	●	●	●
<b>Micron</b>	MT16JTF25664AZ-1G4F1	2GB	DS	Micron	9KF27D9KPT	9	-	●	●	●
<b>MICRON</b>	MT16JTF51264AZ-1G4D1	4GB	DS	MICRON	D9LGK	-	-	●	●	●
<b>OCZ</b>	OCZ3G1333LV3GK	3GB(3 x 1GB)	DS	-	-	9-9-9-20	1.65V			
<b>OCZ</b>	OCZ3F13334GK	4GB(2 x 2GB)	DS	-	-	9-9-9-20	1.7V	●	●	●
<b>OCZ</b>	OCZ3G13334GK	4GB(2 x 2GB)	DS	-	-	9-9-9-20	1.7V			
<b>OCZ</b>	OCZ3G1333LV4GK	4GB(2 x 2GB)	DS	-	-	9-9-9-20	1.65V	●	●	
<b>OCZ</b>	OCZ3P1333LV4GK	4GB(2 x 2GB)	DS	-	-	7-7-7-20	1.65V	●	●	●
<b>OCZ</b>	OCZ3RPX1333EB4GK	4GB(2 x 2GB)	DS	-	-	6-5-5-20	1.85V			
<b>OCZ</b>	OCZ3X13334GK(XMP)	4GB(2 x 2GB)	DS	-	-	7-7-7-20	1.75V	●	●	●
<b>OCZ</b>	OCZ3G1333LV6GK	6GB(3 x 2GB)	DS	-	-	9-9-9-20	1.65V	●	●	
<b>OCZ</b>	OCZ3P1333LV6GK	6GB(3 x 2GB)	DS	-	-	7-7-7-20	1.65V	●		●
<b>OCZ</b>	OCZ3X1333LV6GK(XMP)	6GB(3 x 2GB)	DS	-	-	8-8-8-20	1.60V	●	●	●
<b>OCZ</b>	OCZ3G1333LV8GK	8GB ( 2x 4GB )	DS	-	-	9-9-9-20	1.65V	●	●	●
<b>OCZ</b>	OCZ3RPR1333C9LV8GK	8GB ( 2x 4GB )	DS	-	-	9-9-9-20	1.65V	●		
<b>PSC</b>	AL7F8G73D-DG1	1GB	SS	PSC	A3P1GF3DGF928M9B05	8-8-8-24	1.5V	●	●	●
<b>PSC</b>	AL8F8G73D-DG1	2GB	DS	PSC	A3P1GF3DGF928M9B05	8-8-8-24	1.5V	●	●	●
<b>SAMSUNG</b>	M378B2873DZ1-CH9	1GB	SS	SAMSUNG	SEC 846 HCH9 K4B1G08460	-	-	●	●	●
<b>SAMSUNG</b>	M378B2873EH1-CH9	1GB	SS	Samsung	SEC 913 HCH9 K4B1G0846E	-	-	●	●	●
<b>SAMSUNG</b>	M378B2873FHS-CH9	1GB	SS	SAMSUNG	K4B1G0846F	-	-	●	●	
<b>SAMSUNG</b>	M378B5673DZ1-CH9	2GB	DS	Samsung	K4B1G0846D-HCH9	-	-	●	●	●
<b>SAMSUNG</b>	M378B5673EH1-CH9	2GB	DS	Samsung	SEC 913 HCH9 K4B1G0846E	-	-	●	●	●
<b>SAMSUNG</b>	M378B5673FH0-CH9	2GB	DS	SAMSUNG	K4B1G0846F	-	-	●	●	●
<b>SAMSUNG</b>	M378B5273CH0-CH9	4GB	DS	SAMSUNG	K4B2G0846C	-	-	●	●	●
<b>Super Talent</b>	W1333UA1GH	1GB	SS	HYNIX	H5TQ1G83TFR	9	-	●	●	●
<b>Super Talent</b>	W1333X2GB8(XMP)	1GB	SS	-	-	-	-			
<b>Super Talent</b>	W1333UB2GS	2GB	DS	Samsung	K4B1G0846F	9	-	●	●	●
<b>Super Talent</b>	W1333UB4GS	4GB	DS	Samsung	K4B2G0846C	-	-	●	●	●

<b>Super Talent</b>	W1333UX6GM	6GB(3x 2GB)	DS	Micron	0BF27D9KPT	9-9-9-24	1.5V	●	●	●
<b>Transcend</b>	TS256MLK64V3U	2GB	DS	Micron	9GF27D9KPT	-	-	●	●	●
<b>Transcend</b>	TS256MLK64V3U	2GB	DS	Elpida	J1108BDBG-DJ-F	9	-	●	●	●
<b>Century</b>	PC3-10600 DDR3-1333 9-9-9	1GB	SS	Micron	8FD22D9JNM	-	-			
<b>Century</b>	PC3-10600 DDR3-1333 9-9-9	2GB	DS	Micron	8DD22D9JNM	-	-			
<b>Elixir</b>	M2F2G64CB88B7N-CG	2GB	DS	Elixir	N2CB2G808N-CG	-	-			●
<b>Elixir</b>	M2Y2G64CB8HA9N-CG	2GB	DS	-	-	7-7-7-20	-	●	●	●
<b>Elixir</b>	M2Y2G64CB8HC9N-CG	2GB	DS	Elixir	-	-	-	●	●	●
<b>Elixir</b>	M2F4G64CB8HB5N-CG	4GB	DS	Elixir	N2CB2G808N-CG	-	-	●	●	●
<b>KINGSHARE</b>	KSRPCD313332G	2GB	DS	PATRIOT	PM128M8D385-15	-	-	●	●	●
<b>Kingtiger</b>	2GB DIMM PC3-10666	2GB	DS	Samsung	SEC 904 HCH9 K4B1G0846D	-	-			
<b>Kingtiger</b>	KTG2G1333PG3	2GB	DS	-	-	-	-	●	●	●
<b>PATRIOT</b>	PSD31G13332H	1GB	DS	-	-	9	-	●	●	●
<b>PATRIOT</b>	PSD31G13332	1GB	DS	Patriot	PM64M8D38U-15	-	-	●	●	●
<b>PATRIOT</b>	PSD32G13332H	2GB	DS	-	-	-	-	●	●	●
<b>PATRIOT</b>	PDC34G1333ELK	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.5V			
<b>RAMAXEL</b>	RMR1870ED48E8F-1333	2GB	DS	ELPIDA	J1108BDBG-DJ-F	-	-	●	●	●
<b>SILICON POWER</b>	SP001GBLTU133S01	1GB	SS	NANYA	NT5CB128M8AN-CG	9	-	●	●	●
<b>SILICON POWER</b>	SP001GBLTU133S02	1GB	SS	elixir	N2CB1680AN-C6	9	-	●	●	●
<b>SILICON POWER</b>	SP002GBLTU133S02	2GB	DS	elixir	N2CB1680AN-C6	9	-	●	●	●
<b>TAKEMS</b>	TMS1GB364D081-107EY	1GB	SS	-	-	7-7-7-20	1.5V	●	●	
<b>TAKEMS</b>	TMS1GB364D081-138EY	1GB	SS	-	-	8-8-8-24	1.5V			
<b>TAKEMS</b>	TMS2GB364D081-107EY	2GB	DS	-	-	7-7-7-20	1.5V			
<b>TAKEMS</b>	TMS2GB364D081-138EY	2GB	DS	-	-	8-8-8-24	1.5V			
<b>TAKEMS</b>	TMS2GB364D082-138EW	2GB	DS	-	-	8-8-8-24	1.5V	●	●	
<b>UMAX</b>	E41302GP0-73BDB	2GB	DS	UMAX	U2S24D30TP-13	-	-	●	●	
<b>V-Color</b>	TD2G16C9-Z8	2GB	DS	HYNIX	H5TQ1G83AFP	-	-			
<b>Vendor</b>	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.			
<b>WINTEC</b>	3WVS31333-2G-CNR	2GB	DS	AMPO	AM3420803-13H	-	-	●	●	●

4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports one pair of modules inserted into either the **blue** slots or the **black** slots as one pair of Dual-channel memory configuration
- **4 DIMM:** Supports 4 modules inserted into both the **blue** and **black** slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **blue** slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

## P8Q67-M DO

### DDR3 1600 Qualified Vendors List (QVL)

Vendors	Part No.	Size	SS/DS	Chip Brand	Chip NO.	Timing	Voltage	MM socket support (Optional)		
								1 DIMM	2 DIMM	4 DIMM
A-Data	AD31600E001GM(O)U3K	3GB(3 x 1GB)	SS	-	-	8-8-8-24	1.65V-1.85V			
A-Data	AD31600X002GMU(XMP)	4GB(2 x 2GB)	DS	-	-	7-7-7-20	1.75-1.85V	●	●	
CORSAIR	TR3X3G1600C8D(XMP)	3GB(3 x 1GB)	SS	-	-	8-8-8-24	1.65V	●	●	●
CORSAIR	CMP4GX3M2A1600C8(XMP)	4GB(2 x 2GB)	DS	-	-	8-8-8-24	1.65V	●	●	●
CORSAIR	CMT4GX3M2A1600C6(XMP)	4GB(2 x 2GB)	DS	-	-	6-6-6-20	1.65V	●	●	●
CORSAIR	CMT4GX3M2A1600C7(XMP)	4GB(2 x 2GB)	DS	-	-	7-7-7-20	1.65V	●	●	
CORSAIR	CMX4GX3M2A1600C9(XMP)	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.65V	●	●	●
CORSAIR	CMX4GX3M2A1600C9(XMP)	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.65V	●	●	●
CORSAIR	TR3X6G1600C8 G(XMP)	6GB(3 x 2GB)	DS	-	-	-	-	●	●	●
CORSAIR	TR3X6G1600C8D G(XMP)	6GB(3 x 2GB)	DS	-	-	8-8-8-24	1.65V	●	●	
CORSAIR	TR3X6G1600C8D G(XMP)	6GB(3 x 2GB)	DS	-	-	8-8-8-24	1.65V	●	●	
CORSAIR	TR3X6G1600C9 G(XMP)	6GB(3 x 2GB)	DS	-	-	9-9-9-24	1.65V	●	●	●
CORSAIR	CMX8GX3M4A1600C9(XMP)	8GB(4 x 2GB)	DS	-	-	9-9-9-24	1.65V	●	●	●
Crucial	BL25664BN1608.16FF(XMP)	6GB(3 x 2GB)	DS	-	-	-	-	●	●	
G.SKILL	F3-12800CL9D-2GBNQ(XMP)	2GB(2 x 1GB)	SS	-	-	9-9-9-24	1.5V~1.6V	●	●	●
G.SKILL	F3-12800CL7D-4GBRH(XMP)	4GB(2 x 2GB)	SS	-	-	7-7-7-24	1.6V	●	●	●
G.SKILL	F3-12800CL7D-4GBECO(XMP)	4GB(2 x 2GB)	DS	-	-	7-7-8-24	XMP 1.35V	●	●	●
G.SKILL	F3-12800CL7D-4GBRM(XMP)	4GB(2 x 2GB)	DS	-	-	7-8-7-24	1.6V	●	●	●
G.SKILL	F3-12800CL8D-4GBRM(XMP)	4GB(2 x 2GB)	DS	-	-	8-8-8-24	1.60V	●	●	●
G.SKILL	F3-12800CL9D-4GBECO(XMP)	4GB(2 x 2GB)	DS	-	-	9-9-9-24	XMP 1.35V	●	●	
G.SKILL	F3-12800CL9D-4GBRL(XMP)	4GB(2 x 2GB)	DS	-	-	9-9-9-24	1.5V	●	●	
G.SKILL	F3-12800CL9T-6GBNQ(XMP)	6GB(3 x 2GB)	DS	-	-	9-9-9-24	1.5V~1.6V	●	●	●
G.SKILL	F3-12800CL7D-8GBRH(XMP)	8GB(2 x 4GB)	DS	-	-	7-8-7-24	1.6V	●	●	●
G.SKILL	F3-12800CL8D-8GBECO(XMP)	8GB(2 x 4GB)	DS	-	-	8-8-8-24	XMP 1.35V	●		
G.SKILL	F3-12800CL9D-8GBRL(XMP)	8GB(2 x 4GB)	DS	-	-	9-9-9-24	1.5V		●	
GEIL	GET316GB1600C9QC(XMP)	16GB ( 4x 4GB )	DS	-	-	9-9-9-28	1.6V	●	●	●
GEIL	GV34GB1600C8DC(XMP)	2GB	DS	-	-	8-8-8-28	1.6V			
Kingmax	FLGD45F-B8KG9(XMP)	1GB	SS	Kingmax	KFB8FNGXF-ANX-12A	-	-	●	●	●
Kingmax	FLGD45F-B8MF7 MAEH(XMP)	1GB	SS	-	-	7	-	●	●	●
Kingmax	FLGE85F-B8KG9(XMP)	2GB	DS	Kingmax	KFB8FNGXF-ANX-12A	-	-	●	●	
Kingmax	FLGE85F-B8MF7 MEEH(XMP)	2GB	DS	-	-	7	-			
KINGSTON	KHX1600C9D3K3/12GX(XMP)	12GB(3x4GB)	DS	-	-	9-9-9-27	1.65V	●	●	●
KINGSTON	KVR1600D3N11/2G-ES	2GB	DS	KTC	D1288JPNDPLD9U	11-11-11-28	1.35V-1.5V	●	●	●
KINGSTON	KHX1600C7D3K2/4GX(XMP)	4GB ( 2x 2GB )	DS	-	-	-	1.65V	●	●	●
Kingston	KHX1600C8D3K2/4GX(XMP)	4GB(2 x 2GB)	DS	-	-	8	1.65V	●	●	
Kingston	KHX1600C8D3T1K2/4GX(XMP)	4GB(2 x 2GB)	DS	-	-	8	1.65V	●	●	●
Kingston	KHX1600C9D3K2/4GX(XMP)	4GB(2 x 2GB)	DS	-	-	9	1.65V	●	●	●

<b>Kingston</b>	KHX1600C9D3LK2/4GX(XMP)	4GB(2 x 2GB)	DS	-	-	9	XMP 1.35V	●	●
<b>KINGSTON</b>	KHX1600C9D3T1K3/6GX(XMP)	6GB ( 3x 2GB )	DS	-	-	-	1.65V	●	● ●
<b>Kingston</b>	KHX1600C9D3K3/6GX(XMP)	6GB(3 x 2GB)	DS	-	-	9	1.65V	●	● ●
<b>OCZ</b>	OCZ3G1600LV3GK	3GB(3 x 1GB)	SS	-	-	8-8-8-24	1.65V	●	●
<b>OCZ</b>	OCZ3BE1600C8LV4GK	4GB(2 x 2GB)	DS	-	-	8-8-8-24	1.65V	●	
<b>OCZ</b>	OCZ3BE1600LV4GK	4GB(2 x 2GB)	DS	-	-	7-7-7-24	1.65V	●	● ●
<b>OCZ</b>	OCZ3G16004GK	4GB(2 x 2GB)	DS	-	-	8-8-8-24	1.7V	●	● ●
<b>OCZ</b>	OCZ3G1600LV4GK	4GB(2 x 2GB)	DS	-	-	8-8-8-24	1.65V	●	
<b>OCZ</b>	OCZ3OB1600LV4GK	4GB(2 x 2GB)	DS	-	-	-	1.65V	●	● ●
<b>OCZ</b>	OCZ3P1600EB4GK	4GB(2 x 2GB)	DS	-	-	7-7-6-24	1.8V		
<b>OCZ</b>	OCZ3P1600LV4GK	4GB(2 x 2GB)	DS	-	-	7-7-7-24	1.65V	●	● ●
<b>OCZ</b>	OCZ3P1600LV4GK	4GB(2 x 2GB)	DS	-	-	7-7-7-24	1.65V	●	●
<b>OCZ</b>	OCZ3SOU16004GK	4GB(2 x 2GB)	DS	-	-	8-8-8-24	1.8V		
<b>OCZ</b>	OCZ3G1600LV6GK	6GB(3 x 2GB)	DS	-	-	8-8-8-24	1.65V	●	
<b>Super Talent</b>	WA160UX6G9	6GB(3 x 2GB)	DS	-	-	9	-	●	●
<b>Asint</b>	SLZ3128M8-EGJ1D(XMP)	2GB	DS	Asint	3128M8-GJ1D	9-9-9-24	1.6V		
<b>Elixir</b>	M2Y2G64CB8HA9N-DG(XMP)	2GB	DS	-	-	-	-	●	● ●
<b>Kingtiger</b>	KTG2G1600PG3	2GB	DS	-	-	-	-		
<b>Mushkin</b>	998659(XMP)	6GB(3 x 2GB)	DS	-	-	9-9-9-24	-	●	●
<b>Mushkin</b>	998659(XMP)	6GB(3 x 2GB)	DS	-	-	9-9-9-24	1.5~1.6V		
<b>PATRIOT</b>	PGS34G1600LLKA	4GB(2 x 2GB)	DS	-	-	7-7-7-20	1.7V	●	
<b>Vendor</b>	PartNum.	Size	SS/DS	Chip Brand	ChipNum.	Timing - Dimm	Vol.		

4 DIMM Slots

- **1 DIMM:** Supports one module inserted in any slot as Single-channel memory configuration
- **2 DIMM:** Supports one pair of modules inserted into either the **blue** slots or the **black** slots as one pair of Dual-channel memory configuration
- **4 DIMM:** Supports 4 modules inserted into both the **blue** and **black** slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **blue** slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.