

P8Z77-V PREMIUM Memory Qualified Vendors List (QVL)

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2800(O.C.) MHz capability

| Vendors | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------------|----------------------|-----------------|-------|------------|----------|-------------|---------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| G.skill | F3-2800CL11Q-16GBZHD | 16GB (4x 4GB) | DS | - | - | 11-13-13-35 | 1.65 | • | • | • |

* The 2800Mhz memory modules above are supported by this motherboard; however, the actual frequency support varied depending on the O.C. margin of the installed CPU
 * Due to Intel® 2nd generation processors' behavior, DDR3 2200 and above/2000/1800 MHz memory module will run at DDR3 2133/1866/1600 MHz frequency as default!

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
 We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
 We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overlocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2666(O.C.) MHz capability

| Vendors | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------------|----------------------|-----------------|-------|------------|----------|-------------|---------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| G.skill | F3-2666CL10Q-16GBZHD | 16GB (4x 4GB) | DS | - | - | 10-12-12-31 | 1.65 | • | • | • |

* The 2666Mhz memory modules above are supported by this motherboard; however, the actual frequency support varied depending on the O.C. margin of the installed CPU
 * Due to Intel® 2nd generation processors' behavior, DDR3 2200 and above/2000/1800 MHz memory module will run at DDR3 2133/1866/1600 MHz frequency as default!

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
 We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
 We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overlocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2600(O.C.) MHz capability

| Vendors | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------------|----------------------------|-----------------|-------|------------|----------|-------------|---------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| G.skill | F3-20800CL10Q-16GBZMD(XMP) | 16GB (4x 4GB) | DS | - | - | 10-12-12-28 | 1.65 | • | • | • |
| G.skill | F3-2600CL11Q-32GBZHD | 32GB(4x8GB) | DS | - | - | 11-13-13-35 | 1.65 | • | • | • |

* The 2600Mhz memory modules above are supported by this motherboard; however, the actual frequency support varied depending on the O.C. margin of the installed CPU
 * Due to Intel® 2nd generation processors' behavior, DDR3 2200 and above/2000/1800 MHz memory module will run at DDR3 2133/1866/1600 MHz frequency as default!

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
 We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
 We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overlocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2500(O.C.) MHz capability

| Vendors | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------------|---------------------------|-----------------|-------|------------|----------|-------------|---------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| G.Skill | F3-2000CL10Q-16GBZHD(XMP) | 16GB (4x 4GB) | DS | - | - | 10-11-11-31 | 1.65 | • | • | • |

* The 2500Mhz memory modules above are supported by this motherboard; however, the actual frequency support varied depending on the O.C. margin of the installed CPU
 * Due to Intel® 2nd generation processors' behavior, DDR3 2200 and above/2000/1800 MHz memory module will run at DDR3 2133/1866/1600 MHz frequency as default!

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
 We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
 We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overlocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2400(O.C.) MHz capability

| Vendors | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|------------------|-----------------------------|-----------------|-------|------------|----------|-------------|---------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| CORSAIR | CMGTX3(XMP) | 2GB | DS | - | - | 9-11-9-27 | 1.65 | • | • | • |
| G.SKILL | F3-19200CL10Q-32GBZHD(XMP) | 32GB (4x 8GB) | DS | - | - | 10-12-12-31 | 1.65 | • | • | • |
| G.SKILL | F3-19200CL11Q-16GBZHD(XMP) | 16GB (4x 4GB) | DS | - | - | 11-11-11-31 | 1.65 | • | • | • |
| G.SKILL | F3-19200CL9D-4GBPIS(XMP) | 4G (2x 2G) | DS | - | - | 9-11-9-28 | 1.65 | • | • | • |
| G.SKILL | F3-19200CL9Q-16GBZMD(XMP) | 16GB (4x 4GB) | DS | - | - | 9-11-11-31 | 1.65 | • | • | • |
| GEIL | GOC316GB2400C10QC(XMP) | 16GB (4x 4GB) | DS | - | - | 10-11-11-30 | 1.65 | • | • | • |
| GEIL | GOC316GB2400C11QC(XMP) | 16GB (4x 4GB) | DS | - | - | 11-11-11-30 | 1.65 | • | • | • |
| Kingston | KHX2400C11D3K4/8GX(XMP) | 8GB (4x 2GB) | SS | - | - | 11-13-11-30 | 1.65 | • | • | • |
| Patriot | PVV34G2400C9K(XMP) | 4GB (2x 2GB) | DS | - | - | 9-11-9-27 | 1.66 | • | • | • |
| Transcend | TX2400KLU-4GK (381850)(XMP) | 2GB | DS | - | - | - | 1.65 | • | • | • |

* The 2400Mhz memory modules above are supported by this motherboard; however, the actual frequency support varied depending on the O.C. margin of the installed CPU
 * Due to Intel® 2nd generation processors' behavior, DDR3 2200 and above/2000/1800 MHz memory module will run at DDR3 2133/1866/1600 MHz frequency as default!

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
 We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
 We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overlocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2200(O.C.) MHz capability

| Vendors | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------------|--------------------------|----------------|-------|------------|----------|------------|---------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| G.SKILL | F3-17600CL7D-4GBFLS(XMP) | 4G (2x 2G) | DS | - | - | 7-10-10-28 | 1.65 | • | • | • |
| GEIL | GET34GB2200C9DC(XMP) | 4GB (2x 2GB) | DS | - | - | 9-10-9-28 | 1.65 | • | • | • |

| | | | | | | | | | | |
|----------------|--------------------------|----------------|----|---------|-----|-----------|------|---|---|---|
| GEIL | GET38GB2200C9ADC(XMP) | 8GB (2x 4GB) | DS | - | - | 9-11-9-28 | 1.65 | • | • | • |
| KINGMAX | FLKE85F-B8KJAA-FEIS(XMP) | 4GB (2x 2GB) | DS | Kingmax | N/A | - | - | • | • | • |

* The 2200MHz memory modules above are supported by this motherboard; however, the actual frequency support varied depending on the O.C. margin of the installed CPU.

* Due to Intel® 2nd generation processors' behavior, DDR3 2200 and above/2000/1800 MHz memory module will run at DDR3 2133/1866/1600 MHz frequency as default

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2133(O.C.) MHz capability

| | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|-----------------|-------------------------------|-----------------|-------|------------|----------|-------------|-----------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| A-DATA | AX3U2133C2G9B(XMP) | 2GB | SS | - | - | 9-11-9-27 | 1.55~1.75 | • | • | • |
| A-DATA | AX3U2133GC2G9B(XMP) | 2GB | SS | - | - | 9-9-9-24 | 1.55~1.75 | • | • | • |
| A-DATA | AX3U2133GC4G9B(XMP) | 4GB (4x 4GB) | DS | - | - | 9-11-9-27 | 1.65 | • | • | • |
| Apacer | 78.BAGE4.AF0DC(XMP) | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | - | • | • | • |
| CORSAIR | CMT4GX3M2A2133C9(XMP) | 4GB (2x 2GB) | DS | - | - | 9-10-9-24 | 1.65 | • | • | • |
| CORSAIR | CMT4GX3M2B2133C9(Ver7.1)(XMP) | 4GB (2x 2GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| CORSAIR | CMT4GX3M2B2133C9(XMP) | 4GB (2x 2GB) | DS | - | - | 9-10-9-27 | 1.5 | • | • | • |
| G.SKILL | F3-17000CL11Q2-84GBZLD(XMP) | 64GB (8x 8GB) | DS | - | - | 11-11-11-30 | 1.5 | • | • | • |
| G.SKILL | F3-17000CL9Q-16GBXLD(XMP) | 16GB (4x 4GB) | DS | - | - | 9-11-9-28 | 1.65 | • | • | • |
| G.SKILL | F3-17000CL9Q-16GBZH(XMP) | 16GB (4x 4GB) | DS | - | - | 9-11-10-28 | 1.65 | • | • | • |
| G.SKILL | F3-17066CL9D-8GBPID(XMP) | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.65 | • | • | • |
| G.SKILL | F3-17066CL9Q-16GBTDD(XMP) | 16GB (4x 4GB) | DS | - | - | 9-9-9-24 | 1.65 | • | • | • |
| KINGSTON | KHX2133C11D3K4/16GX(XMP) | 16GB (4x 4GB) | DS | - | - | 11-12-11-30 | 1.65 | • | • | • |
| OCZ | OCZ3XTEP2133C9LV4GK | 2GB | DS | - | - | 7-7-7-20 | 1.65 | • | • | • |
| Patriot | PVV34G2133C9K(XMP) | 4GB (2x 2GB) | DS | - | - | 9-11-9-27 | 1.66 | • | • | • |

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 2000(O.C.) MHz capability

| | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------------------|----------------------------------|-----------------|-------|------------|----------------|-------------|-----------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| A-DATA | AX3U2000GB2G9B(XMP) | 2GB | DS | - | - | 9-11-9-27 | 1.55~1.75 | • | • | • |
| A-DATA | AX3U2000GC4G9B(XMP) | 4GB | DS | - | - | 9-11-9-27 | 1.55~1.75 | • | • | • |
| AEXEA | AXA3ES2G2000L28V(XMP) | 2GB | DS | - | - | - | 1.65 | • | • | • |
| AEXEA | AXA3ES4G2000L28V(XMP) | 4GB (2x 2GB) | DS | - | - | - | 1.65 | • | • | • |
| Apacer | 78.AAGD5.9KD(XMP) | 6GB(3 x 2GB) | DS | - | - | 9-9-9-27 | - | • | • | • |
| Asint | SLA302G08-ML2HB(XMP) | 4GB | DS | Hynix | H5TQ2G83BFRH9C | 9-9-9-27 | - | • | • | • |
| CORSAIR | CMT6GX3M3A2000C8(XMP) | 6GB (3x 2GB) | DS | - | - | 8-9-8-24 | 1.65 | • | • | • |
| CORSAIR | CMZ4GX3M2A2000C10(Ver 5.12)(XMP) | 4GB (2x 2GB) | SS | - | - | 10-10-10-27 | 1.5 | • | • | • |
| G.SKILL | F3-16000CL9D-4GBRH(XMP) | 4GB(2 x 2GB) | DS | - | - | 9-9-9-24 | 1.65 | • | • | • |
| G.SKILL | F3-16000CL9D-4GBTD(XMP) | 4GB(2 x 2GB) | DS | - | - | 9-9-9-24 | 1.65 | • | • | • |
| GEIL | GUP34GB2000C9DC(XMP) | 4GB (2x 2GB) | DS | - | - | 9-9-9-28 | 1.65 | • | • | • |
| Giggle | FA3URSS673A801A | 2GB | DS | - | - | 9-9-9-24 | - | • | • | • |
| Patriot | PV736G2000ELK(XMP) | 6GB (3x 2GB) | DS | - | - | 7-7-7-20 | 1.65 | • | • | • |
| Patriot | PX7312G2000ELK(XMP) | 12GB (3x 4GB) | DS | - | - | 9-11-9-27 | 1.65 | • | • | • |
| Silicon Power | SP002GBLYU2000S02(XMP) | 2GB | DS | - | - | - | - | • | • | • |
| Team | TXD32048M2000C9(XMP) | 2GB | DS | Team | T3D1288RT-20 | 9-9-9-24 | 1.5 | • | • | • |
| Team | TXD32048M2000C9-L(XMP) | 2GB | DS | Team | T3D1288RT-20 | 9-9-9-24 | 1.6 | • | • | • |
| Transcend | TX2000KLN-8GK (388375)(XMP) | 4GB | DS | - | - | - | 1.6 | • | • | • |

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may o

P8Z77-V PREMIUM Motherboard Qualified Vendors Lists (QVL)

DDR3 1866(O.C.) MHz capability

| | Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------------|----------------------------------|-----------------|-------|------------|----------------|-------------|-----------|--------------------------------|--------|--------|
| | | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| A-DATA | AX3U1866GC2G9B(XMP) | 2GB | SS | - | - | 9-11-9-27 | 1.55~1.75 | • | • | • |
| A-DATA | AX3U1866GC4G9B(XMP) | 4GB | DS | - | - | 9-11-9-27 | 1.55~1.75 | • | • | • |
| CORSAIR | CMT32GX3M4X1866C9(Ver3.23)(XMP) | 32GB (4x 8GB) | DS | - | - | 9-10-9-27 | 1.5 | • | • | • |
| CORSAIR | CMZ32GX3M4X1866C10(Ver3.23)(XMP) | 32GB (4x 8GB) | DS | - | - | 10-11-10-27 | 1.5 | • | • | • |
| CORSAIR | CMZ8GX3M2A1866C9(XMP) | 8GB (2x 4GB) | DS | - | - | 9-10-9-27 | 1.5 | • | • | • |
| Crucial | BLE4G3D1869DE1XT0.16FMD(XMP) | 4GB | DS | - | - | 9-9-9-27 | 1.5 | • | • | • |
| G.SKILL | F3-14900CL10Q2-84GBZLD(XMP) | 64GB (8x 8GB) | DS | - | - | 10-11-10-30 | 1.5 | • | • | • |
| G.SKILL | F3-14900CL9D-8GBSR(XMP) | 8GB (2x 4GB) | DS | - | - | 9-10-9-28 | 1.5 | • | • | • |
| G.SKILL | F3-14900CL9Q-16GBXL(XMP) | 16GB (4x 4GB) | DS | - | - | 9-10-9-28 | 1.5 | • | • | • |
| G.SKILL | F3-14900CL9Q-16GBZL(XMP) | 16GB (4x 4GB) | DS | - | - | 9-10-9-28 | 1.5 | • | • | • |
| G.SKILL | F3-14900CL9Q-8GBFLD(XMP) | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.6 | • | • | • |
| Patriot | PXD34G1866ELK(XMP) | 4GB (2x 2GB) | SS | - | - | 9-9-9-24 | 1.65 | • | • | • |
| Patriot | PXD38G1866ELK(XMP) | 8GB (2x 4GB) | DS | - | - | 9-11-9-27 | 1.65 | • | • | • |
| Team | TXD34096M1866HC9K-L(XMP) | 4GB | DS | Hynix | H5TC2G83BFRH9A | 9-11-9-27 | 1.65 | • | • | • |

4 DIMM :

- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
We suggest that you install the module into A2 slot for better stability.
- 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
We suggest that you install the module into A2B2 slot for better stability.
- 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overclocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may o

**P877-V PREMIUM Motherboard Qualified Vendors Lists (QVL)
 DDR3 1800(O.C.) MHz capability**

| Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|---------------------------------|--------------|-------|------------|----------|----------|---------|--------------------------------|--------|--------|
| | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| G.SKILL F3-14400CL9D-4GBRL(XMP) | 4GB(2 x 2GB) | DS | - | - | 9-9-9-24 | 1.6 | • | • | • |

- 4 DIMM :
- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
 We suggest that you install the module into A2 slot for better stability.
 - 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
 We suggest that you install the module into A2B2 slot for better stability.
 - 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overclocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may o

**P877-V PREMIUM Motherboard Qualified Vendors Lists (QVL)
 DDR3 1600MHz capability**

| Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|---|-----------------|-------|------------|----------------|-------------------|-----------|--------------------------------|--------|--------|
| | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |
| A-DATA AM2U16BC2P1 | 2GB | SS | A-DATA | 3CCD-1509A | - | - | • | • | • |
| A-DATA AM2U16BC4P2 | 4GB | DS | A-DATA | 3CCD-1509A | - | - | • | • | • |
| A-DATA AX3U1600PC4G8(XMP) | 4GB | DS | - | - | 8-8-8-24 | 1.55~1.75 | • | • | • |
| AEXEA AXA3PS2G1600S18(XMP) | 2GB | DS | - | - | - | 1.65 | • | • | • |
| Asint SLA302G08-EGG1C(XMP) | 4GB | DS | Asint | 302G08-GG1C | 9-9-9-27 | - | • | • | • |
| Asint SLA302G08-EGJ1C(XMP) | 4GB | DS | Asint | 302G08-GJ1C | 9-9-9-27 | - | • | • | • |
| Asint SLZ3128M8-EGJ1D(XMP) | 2GB | DS | Asint | 3128M8-GJ1D | - | - | • | • | • |
| ATP AQ12M64B8BK0S | 4GB | DS | SAMSUNG | K4B2G08460 | - | NO | • | • | • |
| CORSAIR CMG4GX3M2A1600C6 | 4GB (2x 2GB) | DS | - | - | 6-6-6-18 | 1.65 | • | • | • |
| CORSAIR CML16GX3M4X1600C8(Ver 2.12)(XMP) | 16GB (4x 4GB) | DS | - | - | Heat-Sink Package | 1.5 | • | • | • |
| CORSAIR CMP6GX3M3A1600C8(XMP) | 6GB (3x 2GB) | DS | - | - | 8-8-8-24 | 1.65 | • | • | • |
| CORSAIR CMP6GX3M3A1600C8(XMP) | 6GB (3x 2GB) | DS | - | - | 8-8-8-24 | 1.65 | • | • | • |
| CORSAIR CMX6GX3M3C1600C7(XMP) | 6GB (3x 2GB) | DS | - | - | 7-8-7-20 | 1.65 | • | • | • |
| CORSAIR CMZ16GX3M4A1600C9(XMP) | 16GB (4x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| CORSAIR CMZ32GX3M4X1600C10 (Ver.2.2)(XMP) | 32GB (4x 8GB) | DS | - | - | 10-10-10-27 | 1.5 | • | • | • |
| CORSAIR CMZ8GX3M2A1600C8(XMP) | 8GB (2x 4GB) | DS | - | - | 8-8-8-24 | 1.5 | • | • | • |
| CORSAIR CMZ8GX3M2A1600C9(XMP) | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| CORSAIR CMZ8GX3M4X1600C9(Ver 2.12)(XMP) | 8GB (4x 2GB) | SS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| CORSAIR HX3X12G1600C9(XMP) | 12GB (6x 2GB) | DS | - | - | 9-9-9-24 | 1.6 | • | • | • |
| Crucial BL12864BN1608.8FF(XMP) | 2GB(2x 1GB) | SS | - | - | 8-8-8-24 | 1.65 | • | • | • |
| Crucial BLT4G3D1608DT1TX0.16FM(XMP) | 4GB | DS | - | - | 8-8-8-24 | 1.5 | • | • | • |
| EK Memory EKM324L28BP8-116(XMP) | 4GB(2x 2GB) | DS | - | - | 9 | - | • | • | • |
| Elixir M2X2F64CB88G7N-DG(XMP) | 2GB | SS | Elixir | N2CB2G80GN-DG | 9-9-9-28 | - | • | • | • |
| Elixir M2X4G64CB88G5N-DG(XMP) | 4GB | DS | Elixir | N2CB2G80GN-DG | 9-9-9-28 | - | • | • | • |
| G.SKILL F3-12800CL7D-8GBRH(XMP) | 8GB (2x 4GB) | DS | - | - | 7-8-7-24 | 1.6 | • | • | • |
| G.SKILL F3-12800CL7Q-16GBXH(XMP) | 16GB (4x 4GB) | DS | - | - | 7-8-7-24 | 1.6 | • | • | • |
| G.SKILL F3-12800CL8D-8GBECO(XMP) | 8GB (2x4GB) | DS | - | - | 8-8-8-24 | 1.35 | • | • | • |
| G.SKILL F3-12800CL9D-8GBRL(XMP) | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| G.SKILL F3-12800CL9D-8GBSR2(XMP) | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.25 | • | • | • |
| G.SKILL F3-12800CL9Q-16GBXL(XMP) | 16GB (4x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| G.Skill F3-12800CL9Q-16GBZL(XMP) | 16GB (4x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| GEIL GET316GB1600C9QC(XMP) | 16GB (4x 4GB) | DS | - | - | 9-9-9-28 | 1.6 | • | • | • |
| GEIL GUP34GB1600C7DC(XMP) | 4GB (2x 2GB) | DS | - | - | 7-7-7-24 | 1.6 | • | • | • |
| GoodRam GR1600D364L9/2G | 2GB | DS | GoodRam | GF1008KC-JN | - | - | • | • | • |
| KINGMAX FLGE85F-C8KL9A(XMP) | 2GB | SS | KINGMAX | N/A | 9-9-9-28 | - | • | • | • |
| KINGMAX FLGF65F-C8KL9A(XMP) | 4GB | DS | KINGMAX | N/A | 9-9-9-28 | - | • | • | • |
| KINGSTON KHX1600C9D3K2/4GX(XMP) | 4GB (2x 2GB) | DS | - | - | - | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3K3/12GX(XMP) | 12GB (3x 4GB) | DS | - | - | 9 | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3K3/12GX(XMP) | 12GB (3x 4GB) | DS | - | - | - | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3K3/6GX(XMP) | 6GB (3x 2GB) | DS | - | - | 9 | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3K3/6GX(XMP) | 6GB (3x 2GB) | DS | - | - | 9 | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3K6/24GX(XMP) | 24GB (6x 4GB) | DS | - | - | 9 | 1.65 | • | • | • |
| Kingston KHX1600C9D3K8/32GX(XMP) | 32GB (8x 4GB) | DS | - | - | 9-9-9-27 | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3L2/4GX(XMP) | 4GB (2x 2GB) | DS | - | - | - | 1.35 | • | • | • |
| KINGSTON KHX1600C9D3P1K2/8G | 8GB (2x 4GB) | DS | - | - | 9 | 1.5 | • | • | • |
| KINGSTON KHX1600C9D3T1BK3/12GX(XMP) | 12GB (3x 4GB) | DS | - | - | 9 | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3T1K3/6GX(XMP) | 6GB (3x 2GB) | DS | - | - | 9 | 1.65 | • | • | • |
| KINGSTON KHX1600C9D3X2K2/4GX(XMP) | 4GB (2x 2GB) | DS | - | - | 9 | 1.65 | • | • | • |
| KINGTIGER KTG2G1600PG3(XMP) | 2GB | DS | - | - | - | - | • | • | • |
| Mushkin 996805(XMP) | 4GB (2x 2GB) | DS | - | - | 6-8-6-24 | 1.65 | • | • | • |
| Mushkin 998805(XMP) | 6GB (3x 2GB) | DS | - | - | 6-8-6-24 | 1.65 | • | • | • |
| OCZ OCZ3BE1600CLV4GK | 4GB(2x 2GB) | DS | - | - | 8-8-8 | 1.65 | • | • | • |
| Patriot AE32G1609U1-U | 2GB | SS | AMD | 23EY4587MB6H | - | 1.5 | • | • | • |
| Patriot AE34G1609U2-U | 4GB | DS | AMD | 23EY4587MB6H | - | 1.5 | • | • | • |
| Patriot PGS34G1600LLKA | 4GB(2x 2GB) | DS | - | - | 7-7-7-20 | 1.7 | • | • | • |
| Patriot PGS34G1600LLKA2 | 4GB (2x 2GB) | DS | - | - | 8-8-8-24 | 1.7 | • | • | • |
| Patriot PVV38G1600LLK(XMP) | 8GB (2x 4GB) | DS | - | - | 8-9-8-24 | 1.65 | • | • | • |
| Patriot PX7312G1600LLK(XMP) | 12GB (3x 4GB) | DS | - | - | 8-9-8-24 | 1.65 | • | • | • |
| SanMax SMD-4G68NG-16KK | 4GB | DS | ELPIDA | J2108BDBG-GN-F | - | - | • | • | • |
| Team TXD31024M1600C8-D(XMP) | 1GB | SS | Team | T3D1288RT-16 | 8-8-8-24 | 1.65 | • | • | • |
| Team TXD32048M1600C7-L(XMP) | 2GB | DS | Team | T3D1288T-16 | 7-7-7-24 | 1.65 | • | • | • |
| Team TXD32048M1600H8C-D(XMP) | 2GB | DS | Team | T3D1288RT-16 | 8-8-8-24 | 1.65 | • | • | • |
| Transcend JM1600KLN-8GK | 8GB (2x 4GB) | DS | Transcend | TK483PCW3 | - | - | • | • | • |
| Transcend TS25MLK64V6N | 2GB | SS | Transcend | K4B2G0846C | - | - | • | • | • |
| Transcend TS512MLK64V6N | 4GB | DS | Transcend | K4B2G0846C | - | - | • | • | • |

- 4 DIMM :
- 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration
 We suggest that you install the module into A2 slot for better stability.
 - 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration
 We suggest that you install the module into A2B2 slot for better stability.
 - 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.
 -It is recommended to install the memory modules from the slots for better overclocking capability.
 -The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may o

**P877-V PREMIUM Motherboard Qualified Vendors Lists (QVL)
 DDR3 1333MHz capability**

| Part No. | Size | SS/DS | Chip Brand | Chip NO. | Timing | Voltage | DIMM socket support (Optional) | | |
|----------|------|-------|------------|----------|--------|---------|--------------------------------|--------|--------|
| | | | | | | | 1 DIMM | 2 DIMM | 4 DIMM |

| | | | | | | | | | | |
|---------------|------------------------|---------------|----|-------------|---------------------|------------|-----------|---|---|---|
| A-DATA | AD6311B0823EV | 2GB | SS | A-DATA | 3CCA-1509A | - | - | • | • | • |
| A-DATA | AXDU1333GC2G9(XMP) | 2GB | SS | - | - | 9-9-9-24 | 1.25~1.35 | • | • | • |
| A-DATA | AD6311C1624EV | 4GB | DS | A-DATA | 3CCA-1509A | - | - | • | • | • |
| A-DATA | SU3U1333W8G9(XMP) | 8GB | DS | ELPIDA | J4208BASE-DJ-F | - | - | • | • | • |
| Apacer | 78.A1GC6.9L1 | 2GB | DS | Apacer | AM5D5808FEQSBG | 9 | - | • | • | • |
| Apacer | 78.B1GDE.9L10C | 4GB | DS | Apacer | AM5D5908CEHSBG | 9 | - | • | • | • |
| CORSAIR | TW3X4G1333C9A | 4GB (2x 2GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| CORSAIR | CMX8GX3M2A1333C9(XMP) | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| G.SKILL | F3-10600CL9D-4GBNT | 4GB (2x 2GB) | DS | G.SKILL | D3 128M8CE9 2GB | 9-9-9-24 | 1.5 | • | • | • |
| G.SKILL | F3-10666CL9D-8GBRL | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| G.SKILL | F3-10666CL9D-8GBRL | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| G.SKILL | F3-10666CL9D-8GBXL | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| GEIL | GET316GB1333C9QC | 16GB (4x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| GEIL | GG34GB1333C9DC | 4GB (2x 2GB) | DS | GEIL | GL1L128M88BA115FW | 9-9-9-24 | 1.3 | • | • | • |
| GEIL | GG34GB1333C9DC | 4GB (2x 2GB) | DS | GEIL | GL1L128M88BA15B | 9-9-9-24 | 1.3 | • | • | • |
| GEIL | GVP34GB1333C9DC | 4GB (2x 2GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| GEIL | GB34GB1333C7DC | 4GB(2x 2GB) | DS | GEIL | GL1L128M88BA15FW | 7-7-7-24 | 1.5 | • | • | • |
| GEIL | GVP38GB1333C9DC | 8GB (2x 4GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| GEIL | GVP38GB1333C7QC | 8GB (4x 2GB) | DS | - | - | 7-7-7-24 | 1.5 | • | • | • |
| Hynix | HMT125U6TFR8A-H9 | 2GB | DS | Hynix | H5TC1G83TFR | - | - | • | • | • |
| KINGMAX | FLFE85F-C8KL9 | 2GB | SS | KINGMAX | KFC8FNLF-BGX-12A | - | - | • | • | • |
| KINGMAX | FLFE85F-C8KL9 | 2GB | SS | KINGMAX | KFC8FNLF-DXX-15A | - | - | • | • | • |
| KINGMAX | FLFE85F-C8KM9 | 2GB | SS | Kingmax | KFC8FNMF-BXX-15A | - | - | • | • | • |
| KINGMAX | FLFE85F-B8KL9 | 2GB | DS | KINGMAX | KFB8FNLF-BNF-15A | - | - | • | • | • |
| KINGMAX | FLFF65F-C8KL9 | 4GB | DS | KINGMAX | KFC8FNLF-BGX-12A | - | - | • | • | • |
| KINGMAX | FLFF65F-C8KL9 | 4GB | DS | KINGMAX | KFC8FNLF-DXX-15A | - | - | • | • | • |
| KINGMAX | FLFF65F-C8KM9 | 4GB | DS | Kingmax | KFC8FNMF-BXX-15A | - | - | • | • | • |
| KINGSTON | KVR1333D3S8N9/2G | 2GB | SS | Micron | IFD77 D9L GK | - | 1.5 | • | • | • |
| KINGSTON | KVR1333D3N9/2G | 2GB | DS | Kingston | D1288JPNPLD9U | 9 | 1.5 | • | • | • |
| KINGSTON | KVR1333D3N9K2/4G | 4GB (2x 2GB) | DS | KINGSTON | D1288JEMFPGD9U | - | 1.5 | • | • | • |
| KINGSTON | KVR1333D3E9S/4G | 4GB | DS | Elpida | J2108ECSE-DJ-F | 9 | 1.5 | • | • | • |
| MICRON | MT8JTF25664AZ-1G4M1 | 2GB | SS | MICRON | D9PFC | - | - | • | • | • |
| OCZ | OCZ3G1333LV4GK | 4GB (2x 2GB) | DS | - | - | 9-9-9 | 1.65 | • | • | • |
| OCZ | OCZ3G1333LV8GK | 8GB (2x 4GB) | DS | - | - | 9-9-9 | 1.65 | • | • | • |
| OCZ | OCZ3G1333LV8GK | 8GB (2x 4GB) | DS | - | - | 9-9-9 | 1.65 | • | • | • |
| OCZ | OCZ3RPR1333C9LV8GK | 8GB (2x 4GB) | DS | - | - | 9-9-9 | 1.65 | • | • | • |
| SAMSUNG | M378B5673FH0-CH9 | 2GB | DS | SAMSUNG | K4B1G0846F | - | - | • | • | • |
| SAMSUNG | M378B5273CH0-CH9 | 4GB | DS | SAMSUNG | K4B2G0846C | K4B2G0846C | - | • | • | • |
| SAMSUNG | M378B1G73AH0-CH9 | 8GB | DS | SAMSUNG | K4B4G0846A-HCH9 | - | - | • | • | • |
| Transcend | JM1333KLN-2G (582670) | 2GB | SS | Micron | ICD77 C9L GK | - | - | • | • | • |
| Transcend | JM1333KLN-2G | 2GB | SS | Transcend | TK483PCW3 | - | - | • | • | • |
| Transcend | TS256MLK64V3N (585541) | 2GB | SS | Micron | ICD77 D9L GK | 9 | - | • | • | • |
| Transcend | TS256MLK64V3N (566577) | 2GB | SS | Hynix | H5TQ2G83BFR | 9 | - | • | • | • |
| Transcend | TS256MLK64V3N (574206) | 2GB | SS | Micron | D9L GK | 9 | - | • | • | • |
| Transcend | JM1333KLN-4C (583782) | 4GB | DS | Transcend | TK483PCW3 | 9 | - | • | • | • |
| Transcend | JM1333KLN-4G | 4GB | DS | Transcend | TK483PCW3 | - | - | • | • | • |
| Transcend | TS512MLK64V3N (574831) | 4GB | DS | Micron | D9L GK | 9 | - | • | • | • |
| Transcend | TS1GLK64V3H | 8GB | DS | MICRON | D9PBC | - | - | • | • | • |
| ACTICA | ACT1GHU64B8F1333S | 1GB | SS | SAMSUNG | K4B1G0846F | - | - | • | • | • |
| ACTICA | ACT1GHU72C8G1333S | 1GB | SS | SAMSUNG | K4B1G0846F(ECC) | - | - | • | • | • |
| ACTICA | ACT2GHU64B8G1333M | 2GB | DS | Micron | D9KPT | - | - | • | • | • |
| ACTICA | ACT2GHU64B8G1333S | 2GB | DS | SAMSUNG | K4B1G0846F | - | - | • | • | • |
| ACTICA | ACT2GHU72D8G1333M | 2GB | DS | Micron | D9KPT(ECC) | - | - | • | • | • |
| ACTICA | ACT2GHU72D8G1333S | 2GB | DS | SAMSUNG | K4B1G0846F(ECC) | - | - | • | • | • |
| ACTICA | ACT4GHU64B8H1333H | 4GB | DS | Hynix | H5TQ2G83AFR | - | - | • | • | • |
| ACTICA | ACT4GHU72D8H1333H | 4GB | DS | Hynix | H5TQ2G83AFR(ECC) | - | - | • | • | • |
| ATP | AQ56M72E8BJH9S | 2GB | DS | SAMSUNG | K4B1G0846F(ECC) | - | - | • | • | • |
| ATP | AQ12M72E8BKH9S | 4GB | DS | SAMSUNG | K4B2G0846C(ECC) | - | - | • | • | • |
| BUFFALO | D3U1333-1G | 1GB | SS | Elpida | J1108BFBG-DJ-F | - | - | • | • | • |
| BUFFALO | D3U1333-2G | 2GB | DS | Elpida | J1108BFBG-DJ-F | - | - | • | • | • |
| BUFFALO | D3U1333-4G | 4GB | DS | NANYA | NT5CB256M8BN-CG | - | - | • | • | • |
| EK Memory | EKM324L28BP8-1I3 | 4GB(2x 2GB) | DS | - | - | 9 | - | • | • | • |
| Elixir | M2F2G64CB88B7N-CG | 2GB | SS | Elixir | N2CB2G808N-CG | - | - | • | • | • |
| Elixir | M2F2G64CB88D7N-CG | 2GB | SS | Elixir | M2CB2G88DN-CG | - | - | • | • | • |
| Elixir | M2F4G64CB88B5N-CG | 4GB | DS | Elixir | N2CB2G808N-CG | - | - | • | • | • |
| GoodRam | GR1333D364L9/2G | 2GB | DS | Qimonda | IDSH1G-03A1F1C-13H | - | - | • | • | • |
| KINGTIGER | F10DA2T1880 | 2GB | DS | KINGTIGER | KTG1333PS1208NST-C9 | - | - | • | • | • |
| KINGTIGER | KTG2G1333PG3 | 2GB | DS | - | - | - | - | • | • | • |
| Mach Xtreme | MXD3V13332GS | 2GB | SS | Mach Xtreme | C2S46D30-D313 | - | - | • | • | • |
| Mach Xtreme | MXD3U133316GQ | 16GB (4x 4GB) | DS | - | - | - | - | • | • | • |
| Patriot | AE32G1339U1-U | 2GB | SS | AMD | 23EY4587MB3H | - | 1.5 | • | • | • |
| Patriot | PGD316G1333ELK(XMP) | 16GB (2x 8GB) | DS | - | - | 9-9-9-24 | 1.5 | • | • | • |
| Patriot | PSD32G13332 | 2GB | DS | Patriot | PM128M8D3BU-15 | 9 | - | • | • | • |
| Patriot | PGS34G1333LLKA | 4GB(2x 2GB) | DS | - | - | 7-7-7-20 | 1.7 | • | • | • |
| Patriot | AE34G1339U2-U | 4GB | DS | AMD | 23EY4587MB3H | - | 1.5 | • | • | • |
| Patriot | PG38G1333EL(XMP) | 8GB | DS | - | - | - | 1.5 | • | • | • |
| RiDATA | C304627CB1AG22Fe | 2GB | DS | RiDATA | C304627CB1AG22Fe | 9 | - | • | • | • |
| RiDATA | E304459CB1AG32Cf | 4GB | DS | RiDATA | E304459CB1AG32Cf | 9 | - | • | • | • |
| Silicon Power | SP001GBLTe133S01 | 1GB | SS | NANYA | NT5CB128M8AN-CG | - | - | • | • | • |
| Silicon Power | SP001GBL.TU133S02 | 1GB | SS | S-POWER | 10Y73E5 | 9 | - | • | • | • |
| Silicon Power | SP002GBLTe133S01 | 2GB | DS | NANYA | NT5CB128M8AN-CG | - | - | • | • | • |
| Team | TXD31024M1333C7(XMP) | 1GB | SS | Team | T3D1288LT-13 | 7-7-7-21 | 1.75 | • | • | • |
| Team | TXD31048M1333C7-D(XMP) | 1GB | SS | Team | T3D1288LT-13 | 7-7-7-21 | 1.75 | • | • | • |
| Team | TXD32048M1333C7-D(XMP) | 2GB | DS | Team | T3D1288LT-13 | 7-7-7-21 | 1.5-1.6 | • | • | • |
| Team | TED34096M1333HC9 | 4GB | DS | Team | T3D2568LT-13 | - | - | • | • | • |

4 DIMM :

• 1 DIMM: Supports one module inserted in any slot as Single-channel memory configuration

We suggest that you install the module into A2 slot for better stability.

• 2 DIMM: Supports one pair of modules inserted into either the blue slots or the black slots as one pair of Dual-channel memory configuration

We suggest that you install the module into A2B2 slot for better stability.

• 4 DIMM: Supports 4 modules inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may o