

P7P55 DELUXE Memory Qualified Vendors List (QVL)

P7P55 DELUXE DDR3 1067 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Dimm(Bios)	Voltage	sket support (
CORSAIR	CM3X1024-1066C7	DDR3 1067	1024MB	DS	N/A	Heat-Sink Package	7	1.1	• • •
Crucial	CT12864BA1067.8SFD	DDR3 1067	1024MB	SS	MICRON	D9JNL	7		• • •
Crucial	CT25664BA1067.16SFD	DDR3 1067	2048MB	DS	MICRON	D9JNL	7		• • •
ELPIDA	EBJ10UE8BAW0-AE-E	DDR3 1067	1024MB	SS	ELPIDA	J1108BAGB-DJ-E	7(1066-7-7-7-20)		• • •
ELPIDA	EBJ11RD8BAFA-AE-E	DDR3 1067	1024MB	DS	ELPIDA	J5308BASE-AC-E(ECC)	7		• • •
ELPIDA	EBJ11UD8BAFA-AG-E	DDR3 1067	1024MB	DS	ELPIDA	J5308BASE-AC-E	8		• • •
ELPIDA	EBJ21UE8BAW0-AE-E	DDR3 1067	2048MB	DS	ELPIDA	J1108BAGB-DJ-E	7(1066-7-7-7-20)		• • •
Hynix	HMT112U6AFP8C-G7N0	DDR3 1067	1024MB	SS	HYNIX	H5TQ1G83AFP7G7C	7		• • •
Hynix	HYMT112U64ZNF8-G7	DDR3 1067	1024MB	SS	HYNIX	HY5TQ1G831ZNFP-G7	7		•
Hynix	HMT125U6AFP8C-G7N0	DDR3 1067	2048MB	DS	HYNIX	H5TQ1G83AFP7G7C	7		• • •
Hynix	HYMT125U64ZNF8-G7	DDR3 1067	2048MB	DS	HYNIX	HY5TQ1G831ZNFP-G7	7		• • •
KINGSTON	KVR1066D3N71G	DDR3 1067	1024MB	SS	ELPIDA	J1108BAGB-DJ-E	1066-7-7-7-20	1.5	• • •
KINGSTON	KVR1066D3N72G	DDR3 1067	2048MB	DS	ELPIDA	J1108BAGB-DJ-E	1066-7-7-7-20	1.5	• • •
KINGSTON	KVR1066D3N74G	DDR3 1067	4096MB	DS	SAMSUNG	K4B2G0846B-HCF8	1066-7-7-7-20	1.5	• • •
MICRON	MT8JTF12864AY-1G1D1	DDR3 1067	1024MB	SS	MICRON	7VD22	7		• • •
MICRON	MT8JTF12864AZ-1G1F1	DDR3 1067	1024MB	SS	MICRON	8ZF22 D9KPV	7(1066-7-7-7-20)		• • •
MICRON	MT16JTF25664AY-1G1D1	DDR3 1067	2048MB	DS	MICRON	7VD22	7		• • •
MICRON	MT16JTF25664AZ-1G1F1	DDR3 1067	2048MB	DS	MICRON	8ZF22 D9KPV	7(1066-7-7-7-20)		• • •
SAMSUNG	M378B5273BH1-CF8	DDR3 1067	4096MB	DS	SAMSUNG	K4B2G0846B-HCF8	8(7-7-7-20)	1.5	• •
Transcend	TS256MLK64V1U	DDR3 1067	2048MB	DS	ELPIDA	J1108BAGB-AE-E	7(1066-7-7-7-20)		• • •
Asint	SLY3128M8-EAE	DDR3 1067	1024MB	SS	Asint	DDRIII1208-AE	(7-7-7-20)		• • •
Asint	SLZ3128M8-EAE	DDR3 1067	2048MB	DS	Asint	DDRIII1208-AE	(7-7-7-20)		• • •
Elxir	M2F2G64CB8HAN4-BE	DDR3 1067	2048MB	DS	Elxir	N2CB1G80AN-BE	7		• • •
WINTEC	3DU3191A-10	DDR3 1067	1024MB	DS	Qimonda	IDSH51-03A1F1C-10F	7		• • •

4 Dimm :

- A* : Supports **one module** inserted in any slot as Single-channel memory configuration
- B* : Supports **one pair of modules** inserted into either the blue slots or the black slots as one pair of **Dual-channel** memory configuration
- C* : Supports **4 modules** inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **Blue** slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may operate at a lower frequency than the vendor-marked value.

P7P55 DELUXE Memory Qualified Vendors List (QVL)

P7P55 DELUXE DDR3 1333 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Dimm(Bios)	Voltage	sket support (
A-DATA	AD133301G0U	DDR3 1333	1024MB	SS	A-DATA	AD30908C8D-15IG	1333-9-9-9-24		• • •
A-DATA	AD1333002G0U	DDR3 1333	2048MB	DS	A-DATA	AD30908C8D-15IG	1333-9-9-9-24		• • •
A-DATA	AD31333E002G0U	DDR3 1333	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	7-7-7-20(1333-9-9-9-24)	1.65-1.85	• • •
Apacer	78.01GC6.420	DDR3 1333	1024MB	SS	ELPIDA	J1108BAGB-DJ-E	(1333-9-9-9-24)		• • •
Apacer	78.01GC6.8L0	DDR3 1333	1024MB	SS	Apacer	AMSD5808AEWSBG	9(1333-9-9-9-24)		• • •
Apacer	78.01GC8.422	DDR3 1333	1024MB	SS	ELPIDA	J1108BAGB-DJ-E(ECC)	(1333-9-9-9-24)		• • •
Apacer	78.A1GC6.421	DDR3 1333	2048MB	DS	ELPIDA	J1108BAGB-DJ-E	(1333-9-9-9-24)		• • •
Apacer	78.A1GC6.8L1	DDR3 1333	2048MB	DS	Apacer	AMSD5808AEWSBG	9(1333-9-9-9-24)		• • •
Apacer	78.A1GC8.423	DDR3 1333	2048MB	DS	ELPIDA	J1108BAGB-DJ-E(ECC)	(1333-9-9-9-24)		• • •
CORSAIR	TR3X3G1333C9 (Ver2.1)	DDR3 1333	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	9-9-9-24(1333-9-9-9-24)	1.5	• • •
CORSAIR	CM3X1024-1333C9DHX	DDR3 1333	1024MB	DS	N/A	Heat-Sink Package	(1333-9-9-9-24)	1.1	• •
CORSAIR	Box/PIN:TWIN3X2048-1333C9 (CM3X1024-1333C9)/Ver1.1	DDR3 1333	2048MB(Kit of 2)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.70	• • •
CORSAIR	Box/PIN:TW3X4G1333C9DHX (CM3X2048-1333C9DHX)/Ver3.2	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.70	• •
CORSAIR	TR3X6G1333C9 (Ver2.1)	DDR3 1333	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1333-9-9-9-24)	1.5	• • •
Crucial	CT12864BA1339.8SFD	DDR3 1333	1024MB	SS	MICRON	MT8JF12864AY-1G4D1	(1333-9-9-9-24)		• • •
Crucial	CT25664BA1339.16SFD	DDR3 1333	2048MB	DS	MICRON	D9JNM	(1333-9-9-9-24)		• • •
Crucial	BL25664BA1336.16SFB1	DDR3 1333	4096MB(Kit of 2)	DS	NA	Heat-Sink Package	6-6-6-20(1333-9-9-9-24)	1.8	• • •
ELPIDA	EBJ10UE8BAW0-DJ-E	DDR3 1333	1024MB	SS	ELPIDA	J1108BAGB-DJ-E	9(1333-9-9-9-24)		• •
ELPIDA	EBJ21UE8BAW0-DJ-E	DDR3 1333	2048MB	DS	ELPIDA	J1108BAGB-DJ-E	9(1333-9-9-9-24)		• • •
G.SKILL	F3-10600CL7D-2GBPI	DDR3 1333	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	(1337-7-7-7-18)	1.65	• •
G.SKILL	F3-10600CL8D-2GBHK	DDR3 1333	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	(1337-8-8-8-22)	1.65	• • •
G.SKILL	F3-10666CL7T-4GBPK(XMP)	DDR3 1333	2048MB	DS	N/A	Heat-Sink Package	7-7-7-18(1333-7-7-7-18)	1.5-1.6	• • •
G.SKILL	F3-10666CL8D-4GBHK(XMP)	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	8-8-9-21(1333-7-7-7-20)	1.5-1.6	• • •
G.SKILL	F3-10666CL9T-6GBNQ	DDR3 1333	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1333-9-9-9-24)	1.5	• • •
GEIL	GV34GB1333C7DC	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7-24(1333-8-8-8-28)	1.5	• •
Hynix	HMT112U6BFR8C-H9	DDR3 1333	1024MB	SS	Hynix	H5TQ1G83BFR	9(1333-9-9-9-24)		• • •
Hynix	HMT125U6BFR8C-H9	DDR3 1333	2048MB	DS	Hynix	H5TQ1G83BFR	9(1333-9-9-9-24)		• • •
Hynix	HMT125U6BFR8C-H9	DDR3 1333	2048MB	DS	Hynix	H5TQ1G83BFRH9C	9(1333-9-9-9-24)		• • •
KINGMAX	FLFD45F-B8EE9	DDR3 1333	1024MB	SS	ELPIDA	J1108BASE-DJ-E	(1333-9-9-9-24)		• • •
KINGSTON	KVR1333D3N9/1G	DDR3 1333	1024MB	SS	ELPIDA	J1108BAGB-DJ-E	9(1066-8-7-7-20)	1.5	• • •
KINGSTON	KVR1333D3N9/2G	DDR3 1333	2048MB	DS	ELPIDA	J1108BAGB-DJ-E	1333-9-9-9-24	1.5	• • •
KINGSTON	KVR1333D3N9/2G	DDR3 1333	2048MB	DS	ELPIDA	J1108BAGB-DJ-E	9(1066-8-7-7-20)	1.5	• • •
MICRON	MT8JTF12864AY-1G4BYES	DDR3 1333	1024MB	SS	MICRON	Z9HWR	(1333-9-9-9-24)		• •
MICRON	MT8JTF12864AZ-1G4F1	DDR3 1333	1024MB	SS	MICRON	9FF22 D9KPT	9(1066-8-8-8-20)		• • •
MICRON	MT16JTF25664AZ-1G4F1	DDR3 1333	2048MB	DS	MICRON	9FF22 D9KPT	9(1066-8-8-8-20)		• • •
OCZ	OC23G1333LV3GK	DDR3 1333	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	9-9-9(1066-7-7-7-20)	1.65	• •
OCZ	OC23P1333LV3GK	DDR3 1333	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	7-7-7(1066-7-7-7-16)	1.65	• • •
OCZ	OC23P1333ZGK	DDR3 1333	1024MB	DS	N/A	Heat-Sink Package	7-7-7-20(1333-9-9-9-24)		• •

OCZ	OC23G13334GK	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	9(1066-8-9-9-20)	1.7	• • •
OCZ	OC23P13334GK	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7(1333-7-7-7-20)	1.8	• • •
OCZ	OC23RPX1333EB4GK	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	(1066-6-6-5)	1.85	• • •
OCZ	OC23G1333LV6GK	DDR3 1333	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9(1066-7-7-20)	1.65	• • •
OCZ	OC23P1333LV6GK	DDR3 1333	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	7-7-7(1066-7-7-20)	1.65	• • •
OCZ	OC2X1333LV6GK(XMP)	DDR3 1333	6144MB(Kit of 3)	DS	NA	Heat-Sink Package	8-8-8(1066-7-7-16)	1.6	• • •
SAMSUNG	M378B2873DZ1-CH9	DDR3 1333	1024MB	SS	SAMSUNG	K4B1G0846D	9(1333-9-9-9-24)		• • •
SAMSUNG	M378B2873EH1-CH9	DDR3 1333	1024MB	SS	SAMSUNG	K4B1G0846E	1066-8-7-7-20		• • •
SAMSUNG	M391B2873DZ1-CH9	DDR3 1333	1024MB	SS	SAMSUNG	K4B1G0846D(ECC)	9(1333-9-9-9-24)		• • •
SAMSUNG	M378B5673DZ1-CH9	DDR3 1333	2048MB	DS	SAMSUNG	K4B1G0846D	9(1333-9-9-9-24)		• • •
SAMSUNG	M378B5673EH1-CH9	DDR3 1333	2048MB	DS	SAMSUNG	K4B1G0846E	1066-8-7-7-20		• • •
SAMSUNG	M391B5673DZ1-CH9	DDR3 1333	2048MB	DS	SAMSUNG	K4B1G0846D(ECC)	9(1333-9-9-9-24)		• • •
SAMSUNG	M378B5273BH1-CH9	DDR3 1333	4096MB	DS	SAMSUNG	K4B2G0846B-HCH9	9(1333-9-9-9-24)		• • •
Super Talent	W1333UX2GB(XMP)	DDR3 1333	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	8(1333-8-8-8-24)	1.8	• • •
Transcend	TS128MLK64V3U	DDR3 1333	1024MB	SS	SAMSUNG	K4B1G0846D	9(1333-9-9-9-24)		• • •
Transcend	TS256MLK64V3U	DDR3 1333	2048MB	DS	SAMSUNG	K4B1G0846D	9(1333-9-9-9-24)		• • •
Asint	SLY3128M8-EDJ	DDR3 1333	1024MB	SS	Asint	DDR111208-DJ	(9-9-9-24)		• • •
Asint	SLY3128M8-EDJE	DDR3 1333	1024MB	SS	ELPIDA	J1108BASE-DJ-E	1066-8-8-8-20		• • •
Asint	SLZ3128M8-EDJ	DDR3 1333	2048MB	DS	Asint	DDR111208-DJ	(9-9-9-24)		• • •
Asint	SLZ3128M8-EDJE	DDR3 1333	2048MB	DS	ELPIDA	J1108BASE-DJ-E	1066-8-8-8-20		• • •
ASUS	N/A	DDR3 1333	1024MB	DS	N/A	Heat-Sink Package	(1333-9-9-9-24)		• • •
BUFFALO	FSX133D3G-1G	DDR3 1333	1024MB	SS	N/A	Heat-Sink Package	(1066-7-7-7-20)		• • •
BUFFALO	FSH133D3G-T3G(XMP)	DDR3 1333	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	7-7-7-20(1066-6-7-7-20)		• • •
BUFFALO	FSX133D3G-2G	DDR3 1333	2048MB	DS	N/A	Heat-Sink Package	(1066-7-7-7-20)		• • •
Elxir	M2F2G64C88HA4N-CG	DDR3 1333	2048MB	DS	Elxir	N2CB1G80AN-CG	(1333-9-9-9-24)		• • •
Patriot	POC32G1333LLK	DDR3 1333	1024MB	SS	PATRIOT	Heat-Sink Package	7(1337-7-7-7-20)	1.7	• • •
Patriot	PVT33G1333ELK	DDR3 1333	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.65	• • •
Patriot	PV334G1333ELK	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.5	• • •
Patriot	PV334G1333LLK	DDR3 1333	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7-20(1066-7-7-7-20)	1.7	• • •
Patriot	PVT36G1333ELK	DDR3 1333	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.65	• • •
Silicon Power	SP001GBLTU133S02	DDR3 1333	1024MB	SS	S-POWER	I0YT3E0	9(1333-9-9-9-24)		• • •
Silicon Power	SP002GBLTU133S02	DDR3 1333	2048MB	DS	S-POWER	I0YT3E0	9(1333-9-9-9-24)		• • •

4 Dimm :

- A*: Supports **one module** inserted in any slot as Single-channel memory configuration
- B*: Supports **one pair of modules** inserted into either the blue slots or the black slots as one pair of **Dual-channel** memory configuration
- C*: Supports **4 modules** inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **Blue** slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may operate at a lower frequency than the vendor-marked value.

P7P55 DELUXE Memory Qualified Vendors List (QVL)

P7P55 DELUXE DDR3 1600 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Dimm(Bios)	Voltage	Slot support (A*, B*, C*)
A-DATA	AD31600E001GMU	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	8-8-8-24(1333-9-9-9-24)	1.65-1.85	• • •
A-DATA	AD31600F002GMU(XMP)	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	7-7-7-20(1333-9-9-9-24)	1.75-1.85	• • •
CORSAIR	TR3X3G1600C8D(XMP)/Ver2.1	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	8-8-8-24(1601-8-8-8-24)	1.65	• • •
CORSAIR	TR3X3G1600C8D	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	8-8-8-24(1600-8-8-8-24)	1.65	• • •
CORSAIR	TR3X3G1600C9(XMP)/Ver1.1	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	9-9-9-24(1601-9-9-9-24)	1.65	• • •
CORSAIR	Box/P/N:TW3X4G1600C9DHXNV/ (CM3X2G1600C9DHXNV)/Ver4.1	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	(1333-9-9-9-24)	1.80	• • •
CORSAIR	TR3X6G1600C8D(XMP)/Ver2.1	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8-24(1601-8-8-8-24)	1.65	• • •
CORSAIR	TR3X6G1600C8D	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8-24(1600-8-8-8-24)	1.65	• • •
CORSAIR	TR3X6G1600C9(XMP)/Ver2.1	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1333-9-9-9-24)	1.65	• • •
Crucial	BL12864B41608.8SFB(XMP)	DDR3 1600	1024MB	SS	N/A	Heat-Sink Package	(1601-8-8-8-24)	1.8	• • •
G.SKILL	F3-12800CL9D-2GBNQ	DDR3 1600	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	(1333-9-9-9-24)	1.6	• • •
G.SKILL	F3-12800CL8T-6GBHX(XMP)	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8-21(1333-8-8-8-21)	1.6-1.65	• • •
G.SKILL	F3-12800CL8T-6GBPI(XMP)	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8-21(1066-8-8-8-20)	1.6-1.65	• • •
G.SKILL	F3-12800CL9T-6GBNQ	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1601-9-9-9-24)	1.5-1.6	• • •
GEIL	GV34GB1600C8DC	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	8-8-8-28(1600-8-8-8-28)	1.6	• • •
KINGMAX	FLGD45F-B8KG9-NAES	DDR3 1600	1024MB	SS	KINGMAX	KFB8FNGXF-ANX-12A	9(1600-9-8-8-28)	1.5	• • •
KINGMAX	FLGE85F-B8KG9-NEES	DDR3 1600	2048MB	DS	KINGMAX	KFB8FNGXF-ANX-12A	9(1600-9-8-8-28)	1.5	• • •
KINGSTON	KHX12800D3LLK3/GGX(XMP)	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	1600-8-8-8-20	1.65	• • •
KINGSTON	KHX12800D3K2/4G	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	9(1333-9-9-9-24)	1.9	• • •
KINGSTON	KHX12800D3LLK3/GGX(XMP)	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	(1066-8-8-8-20)	1.65	• • •
OCZ	OC23P1600EB1G	DDR3 1600	1024MB	SS	N/A	Heat-Sink Package	7-6-6-24(1333-7-7-7-20)		• • •
OCZ	OC23G1600LV3GK	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	8-8-8(1066-7-7-7-20)	1.65	• • •
OCZ	OC23P1600LV3GK	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	7-7-7(1066-7-7-7-20)	1.65	• • •
OCZ	OC23P1600Q4GK	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7(1333-7-7-7-20)	1.9	• • •
OCZ	OC23P1600EB4GK	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-6(1333-7-7-7-20)	1.8	• • •
OCZ	OC23G1600LV6GK	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8(1066-7-7-7-20)	1.65	• • •
OCZ	OC23G1600LV6GK	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8(1066-7-7-7-16)	1.65	• • •
OCZ	OC23X1600LV6GK(XMP)	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8(1600-8-8-8-24)	1.65	• • •
OCZ	OC23X1600LV6GK(XMP)	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8-8-8(1066-7-7-7-16)	1.65	• • •
Cell Shock	CS322271	DDR3 1600	2048MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7-14(1066-7-7-7-20)	1.7-1.9	• • •
Elxir	M2F2G64C88HA4N-DG	DDR3 1600	2048MB	DS	Elxir	N2CB1G80AN-DG	9(1333-9-9-9-28)		• • •
Mushkin	996657	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7-20		• • •

Mushkin	99859	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1333-9-9-9-24)	1.5-1.6	• • • •
Patriot	PVT3G1600ELK	DDR3 1600	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.65	• • • •
Patriot	PVS34G1600ELK	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.8	• • • •
Patriot	PVS34G1600LLK	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7-20(1066-7-7-7-20)	1.9	• • • •
Patriot	PVS34G1600LLKN	DDR3 1600	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7-20(1066-7-7-7-20)	2.0	• • • •
Patriot	PVT36G1600ELK	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	1.65	• • • •
Patriot	PVT36G1600ELK	DDR3 1600	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1600-7-7-7-20)	1.65	• • • •
PQI	MFADR401PA0102(XMP)	DDR3 1600	2048MB	DS	SAMSUNG	K4B1G08460	1066-8-8-8-20		• • • •

4 Dimm :

- A*: Supports **one module** inserted in any slot as Single-channel memory configuration
- B*: Supports **one pair of modules** inserted into either the blue slots or the black slots as one pair of **Dual-channel** memory configuration
- C*: Supports **4 modules** inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **Blue** slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may operate at a lower frequency than the vendor-marked value.

P7P55 DELUXE Memory Qualified Vendors List (QVL)

P7P55 DELUXE DDR3 1625 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Dimm(Bios)	Voltage	cket support (A* B* C*)
KINGSTON	KHX13000D3LLK2GQ(EPP)	DDR3 1625	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package		1.9	• • • •
KINGSTON	KHX13000D3LLK2GQ(XMP)	DDR3 1625	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package		1.9	• • • •
KINGSTON	KHX13000D3LLK2GQXN	DDR3 1625	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package		1.9	• • • •

4 Dimm :

- A*: Supports **one module** inserted in any slot as Single-channel memory configuration
- B*: Supports **one pair of modules** inserted into either the blue slots or the black slots as one pair of **Dual-channel** memory configuration
- C*: Supports **4 modules** inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **Blue** slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may operate at a lower frequency than the vendor-marked value.

P7P55D DELUXE Memory Qualified Vendors List (QVL)

P7P55D DELUXE DDR3 1800 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Dimm(Bios)	Voltage	cket support (A* B* C*)
Apacer	78.0AGCD-CD2(XMP)	DDR3 1800	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	8-8-8-24(1800-8-8-8-24)	1.8	• • • •
CORSAIR	BoxPiN-TW3X4G1800C8DF (CM3X2G1800C8D)Ver4.1	DDR3 1800	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	8-8-8-24	1.80	• • • •
KINGSTON	KHX14400D31G	DDR3 1800	1024MB	SS	N/A	Heat-Sink Package		1.9	• • • •
KINGSTON	KHX14400D3K22GQ(EPP)	DDR3 1800	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package		1.9	• • • •
KINGSTON	KHX14400D3K33GX(XMP)	DDR3 1800	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	1800-9-9-9-27	1.65	• • • •
OCZ	OCZ3P18002GK	DDR3 1800	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	8		• • • •
OCZ	OCZ3P18004GK	DDR3 1800	4096MB(Kit of 2)	DS	N/A	Heat-Sink Package	8	1.9	• • • •
Transcend	TX1800KLU-2GQ(XMP)	DDR3 1800	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	8		• • • •
Patriot	PVS32G1800LLKN(EPP)	DDR3 1800	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	8-8-8-20(1066-7-7-7-20)	1.9	• • • •

4 Dimm :

- A*: Supports **one module** inserted in any slot as Single-channel memory configuration
- B*: Supports **one pair of modules** inserted into either the blue slots or the black slots as one pair of **Dual-channel** memory configuration
- C*: Supports **4 modules** inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **Blue** slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may operate at a lower frequency than the vendor-marked value.

P7P55 DELUXE Memory Qualified Vendors List (QVL)

P7P55 DELUXE DDR3 2000 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Dimm(Bios)	Voltage	cket support (A* B* C*)
Apacer	78.0AGCQ.CB2(XMP)	DDR3 2000	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	9-9-9-27(1066-8-8-8-20)		• • • •
Crucial	BL12864BE2009.8SF83(EPP)	DDR3 2000	1024MB	SS	N/A	Heat-Sink Package	9-9-9-28(1333-9-9-9-24)	2	• • • •
G.SKILL	F3-16000CL7T-6GBPS(XMP)	DDR3 2000	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	7-8-7-20(1066-8-8-8-20)	1.65	• • • •
G.SKILL	F3-16000CL9T-6BPS(XMP)	DDR3 2000	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-8-8-8-20)	1.65	• • • •
KINGSTON	KHX16000D3K22GQ(EPP)	DDR3 2000	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package		2.0	• • • •
KINGSTON	KHX16000D3K33GX(XMP)	DDR3 2000	3072MB(Kit of 3)	SS	N/A	Heat-Sink Package	9(1333-9-9-9-24)	1.65	• • • •
KINGSTON	KHX16000D3ULT1K36GX(XMP)	DDR3 2000	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	8(1066-8-8-8-20)	1.65	• • • •
KINGSTON	KHX16000D3T1K36GX(XMP)	DDR3 2000	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9(1066-8-8-8-20)	1.65	• • • •
OCZ	OCZ3FXT2002GK	DDR3 2000	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	8	1.9	• • • •
OCZ	OCZ3P2002GK(EPP)	DDR3 2000	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	9	1.9	• • • •
OCZ	OCZ3P2000EB2GK	DDR3 2000	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	9-8-8(1066-8-7-7-20)	1.8	• • • •
Giggle	9CAASS37AZ201D1	DDR3 2000	2048MB	DS	N/A	Heat-Sink Package	9-9-9-24		• • • •
Patriot	PVS32G2000LLKN	DDR3 2000	2048MB(Kit of 2)	SS	N/A	Heat-Sink Package	9-9-9-24(1066-7-7-7-20)	2	• • • •

4 Dimm :

- A*: Supports **one module** inserted in any slot as Single-channel memory configuration
- B*: Supports **one pair of modules** inserted into either the blue slots or the black slots as one pair of **Dual-channel** memory configuration
- C*: Supports **4 modules** inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **Blue** slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may operate at a lower frequency than the vendor-marked value.

P7P55 DELUXE Memory Qualified Vendors List (QVL)

P7P55 DELUXE DDR3 2133 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Dimm(Bios)	Voltage	cket support (A* B* C*)
G.SKILL	F3-17066CL9T-6GB-T	DDR3 2133	6144MB(Kit of 3)	DS	N/A	Heat-Sink Package	9-9-9-24(1066-8-7-7-20)	1.65	• • • •

4 Dimm :

- A*: Supports **one module** inserted in any slot as Single-channel memory configuration
- B*: Supports **one pair of modules** inserted into either the blue slots or the black slots as one pair of **Dual-channel** memory configuration
- C*: Supports **4 modules** inserted into both the blue and black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the **Blue** slots for better overlocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overlocking may operate at a lower frequency than the vendor-marked value.