

P6T DELUXE V2 Memory Qualified Vendors List (QVL)

P6T DELUXE V2 DDR3 1067 Qualified Vendors List (QVL)												
Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Lable(Bios)	Voltage	DIMM socket support (Optional)			
									A*	B*	C*	D*
Crucial	CT12864BA1067.8FF	DDR3 1067	1GB	SS	MICRON	D9KPT	7(1066-7-7-7-20)	N/A	●	●	●	●
Crucial	CT12872BA1067.9FF	DDR3 1067	1GB	SS	MICRON	D9KPT(ECC)	7(1066-9-9-9-25)	N/A	●	●	●	●
Crucial	CT25664BA1067.16FF	DDR3 1067	2GB	DS	MICRON	D9KPT	7(1066-7-7-7-20)	N/A	●	●	●	●
Crucial	CT25672BA1067.18FF	DDR3 1067	2GB	DS	MICRON	D9KPT(ECC)	7(1066-7-7-7-20)	N/A	●	●	●	●
MICRON	MT8JTF12864AZ-1G1F1	DDR3 1067	1GB	SS	MICRON	8ZF22 D9KPV	7(1066-7-7-7-20)	N/A	●	●	●	●
MICRON	MT8JTF12864AZ-1G1F1	DDR3 1067	1GB	SS	MICRON	D9KPT	7(1066-7-7-7-20)	N/A	●	●	●	●
MICRON	MT9JSF12872AZ-1G1F1	DDR3 1067	1GB	SS	MICRON	D9KPT(ECC)	7(1066-9-9-9-25)	N/A	●	●	●	●
MICRON	MT16JTF25664AZ-1G1F1	DDR3 1067	2GB	DS	MICRON	8ZF22 D9KPV	7(1066-7-7-7-20)	N/A	●	●	●	●
MICRON	MT16JTF25664AZ-1G1F1	DDR3 1067	2GB	DS	MICRON	D9KPT	7(1066-7-7-7-20)	N/A	●	●	●	●
MICRON	MT18JSF25672AZ-1G1F1	DDR3 1067	2GB	DS	MICRON	D9KPT(ECC)	7(1066-7-7-7-20)	N/A	●	●	●	●
Elixir	M2Y2G64CB8HA9N-BE	DDR3 1067	2GB	DS	N/A	Heat-Sink Package	(1066-7-7-7-20)	N/A	●		●	●
KINGSOTN	KVR1066D3N7/1G	DDR3 1067	1GB	SS	KINGSTON	D1288JEKAPA7U	7(1067-7-7-7-20)	1.5	●	●	●	●
KINGSOTN	KVR1066D3N7/2G	DDR3 1067	2GB	DS	KINGSTON	D1288JEKAPGA7U	7(1067-7-7-7-20)	1.5	●	●	●	●

- 6 Dimm :
- **A\***: Supports [two \(2\) modules](#) inserted into slot A1 and B1 as one pair of Dual-channel memory configuration
  - **B\***: Supports [three \(3\) modules](#) inserted into the orange slots (A1, B1 and C1) as one set of Triple-channel memory configuration
  - **C\***: Supports [four \(4\) modules](#) inserted into the orange slots (A1, B1 and C1) and the black slot A2 as one set of Triple-channel memory configuration
  - **D\***: Supports [six \(6\) modules](#) inserted into both the orange slots and the black slots as two set of Triple-channel memory configuration.

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.  
-It is recommended to install the memory modules from the orange slots for better overclocking capability.  
-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

P6T DELUXE V2 Memory Qualified Vendors List (QVL)

P6T DELUXE V2 DDR3 1333 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Lable(Bios)	Voltage	DIMM socket support (Optional)			
A-DATA	AD3U1333C4G9-B	DDR3 1333	4GB	DS	Hynix	H5TQ2G83AFRH9C	1333-9-9-9-24	N/A	●	●	●	●
Crucial	CT12864BA1339.8FF	DDR3 1333	1GB	SS	MICRON	D9KPT	9(1333-9-9-9-24)	N/A	●	●	●	●
Crucial	CT12872BA1339.9FF	DDR3 1333	1GB	SS	MICRON	D9KPT(ECC)	9(1333-9-9-9-24)	N/A	●	●		
Crucial	BL25664BN1337.16FF(XMP)	DDR3 1333	2GB	DS	N/A	Heat-Sink Package	7-7-7-24 (1333-9-9-9-24)	1.65	●	●	●	●
Crucial	CT25664BA1339.16FF	DDR3 1333	2GB	DS	MICRON	D9KPT	9(1333-9-9-9-24)	N/A	●	●	●	●
Crucial	CT25672BA1339.18FF	DDR3 1333	2GB	DS	MICRON	D9KPT(ECC)	9(1333-9-9-9-24)	N/A	●	●	●	●
KINGSTON	KVR1333D3N9/1G	DDR3 1333	1GB	SS	Hynix	H5TQ1G83BFR	9(1333-9-9-9-24)	1.5	●	●	●	●
KINGSTON	KVR1333D3N9/1G	DDR3 1333	1GB	SS	ELPIDA	J1108BABG-DJ-E	9(1066-8-7-7-20)	1.5	●	●	●	●
KINGSTON	KVR1333D3N9/2G	DDR3 1333	2GB	DS	Qimonda	IDSH1G-03A1F1C-13H	9(1333-9-9-9-24)	1.5	●	●	●	●
MICRON	MT8JTF12864AZ-1G4F1	DDR3 1333	1GB	SS	MICRON	9FF22 D9KPT	9(1066-8-8-8-20)	N/A	●	●	●	●
MICRON	MT8JTF12864AZ-1G4F1	DDR3 1333	1GB	SS	MICRON	D9KPT	9(1333-9-9-9-24)	N/A	●	●	●	●
MICRON	MT9JSF12872AZ-1G4F1	DDR3 1333	1GB	SS	MICRON	D9KPT(ECC)	9(1333-9-9-9-24)	N/A	●	●		
MICRON	MT16JF25664AZ-1G4F1	DDR3 1333	2GB	DS	MICRON	D9KPT	9(1333-9-9-9-24)	N/A	●	●	●	●
MICRON	MT16JTF25664AZ-1G4F1	DDR3 1333	2GB	DS	MICRON	9FF22 D9KPT	9(1066-8-8-8-20)	N/A	●	●	●	●
MICRON	MT18JSF25672AZ-1G4F1	DDR3 1333	2GB	DS	MICRON	D9KPT(ECC)	9(1333-9-9-9-24)	N/A	●	●	●	●
OCZ	OCZ31333LV6GK(XMP)	DDR3 1333	6GB(3 x 2GB)	DS	NA	Heat-Sink Package	8-8-8(1066-7-7-7-16)	1.6	●	●	●	●
SAMSUNG	M378B2873EH1-CH9	DDR3 1333	1GB	SS	SAMSUNG	K4B1G0846E	(1066-8-7-7-20)	N/A	●	●	●	●
SAMSUNG	M378B5673EH1-CH9	DDR3 1333	2GB	DS	SAMSUNG	K4B1G0846E	(1066-8-7-7-20)	N/A	●	●	●	●
Asint	SLY3128M8-EDJE	DDR3 1333	1GB	SS	ELPIDA	J1108BASE-DJ-E	(1066-8-8-8-20)	N/A	●	●	●	●
Asint	SLZ3128M8-EDJE	DDR3 1333	2GB	DS	ELPIDA	J1108BASE-DJ-E	(1066-8-8-8-20)	N/A	●	●	●	●
ATP	AQ28M64A8BJH9S	DDR3 1333	1GB	SS	SAMSUNG	K4B1G0846E	(1333-9-9-9-24)	N/A	●	●	●	●
ATP	AQ28M72D8BJH9S	DDR3 1333	1GB	SS	SAMSUNG	K4B1G0846D(ECC)	(1333-9-9-9-24)	N/A	●	●	●	●
ATP	AQ56M64B8BJH9S	DDR3 1333	2GB	DS	SAMSUNG	K4B1G0846D	(1333-9-9-9-24)	N/A	●	●	●	●
ATP	AQ56M72E8BJH9S	DDR3 1333	2GB	DS	SAMSUNG	K4B1G0846D(ECC)	(1333-9-9-9-24)	N/A	●	●	●	●
BUFFALO	FSH1333D3G-T3G(XMP)	DDR3 1333	3GB(3 x 1GB)	SS	N/A	Heat-Sink Package	7-7-7-20(1066-8-7-7-20)	N/A	●	●	●	●
Elixir	M2Y2G64CB8HA9N-CG	DDR3 1333	2GB	DS	N/A	Heat-Sink Package	(1333-7-7-7-20)	N/A	●	●	●	●

- 6 Dimm :
- **A\***: Supports [two \(2\) modules](#) inserted into slot A1 and B1 as one pair of Dual-channel memory configuration
  - **B\***: Supports [three \(3\) modules](#) inserted into the orange slots (A1, B1 and C1) as one set of Triple-channel memory configuration
  - **C\***: Supports [four \(4\) modules](#) inserted into the orange slots (A1, B1 and C1) and the black slot A2 as one set of Triple-channel memory configuration
  - **D\***: Supports [six \(6\) modules](#) inserted into both the orange slots and the black slots as two set of Triple-channel memory configuration.

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.  
-It is recommended to install the memory modules from the orange slots for better overclocking capability.  
-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

P6T DELUXE V2 Memory Qualified Vendors List (QVL)

P6T DELUXE V2 DDR3 1600 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Lable(Bios)	Voltage	MM socket support (Optional)		
A-DATA	AD31600G001GMU	DDR3 1600	1GB	SS	N/A	Heat-Sink Package	9-9-9-24 (1333-8-8-8-24)	1.65~1.85	●	●	●
A-DATA	AX3U1600GB2G9-3G(XMP)	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	9-9-9-24 (1600-9-9-9-24)	1.65~1.85	●	●	●
Crucial	BL25664BN1608.16FF(XMP)	DDR3 1600	2GB	DS	N/A	Heat-Sink Package	8-8-8-24 (1333-9-9-9-24)	1.65	●	●	●
G.SKILL	F3-12800CL8T-6GBPI(XMP)	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	8-8-8-21(1066-8-8-8-20)	1.6~1.65	●	●	●
KINGSTON	KHX1600C9D3K3/12GX(XMP)	DDR3 1600	12GB(3 x 4GB)	DS	N/A	Heat-Sink Package	(1066-7-7-7-20)	1.65	●	●	●
KINGSTON	KHX1600C9D3K3/6GX(XMP)	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	9(1333-9-9-9-24)	1.65	●	●	●
OCZ	OCZ3P1600LV4GK	DDR3 1600	4GB(2 x 2GB)	DS	N/A	Heat-Sink Package	7-7-7(1067-7-7-7-20)	1.65	●		
OCZ	OCZ3X16004GK(XMP)	DDR3 1600	4GB(2 x 2GB)	DS	N/A	Heat-Sink Package	7-7-7(1066-7-7-7-16)	1.9		●	●
OCZ	OCZ3FXE1600C7LV6GK	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	7-7-7(1066-9-9-9-24)	1.65	●	●	
OCZ	OCZ3G1600LV6GK	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	8-8-8(1066-7-7-7-16)	1.65	●	●	
OCZ	OCZ3X1600LV6GK(XMP)	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	8-8-8(1066-7-7-7-16)	1.65	●	●	●
Super Talent	WB160UX6GB(XMP)	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	(1333-8-8-8-24)	N/A	●	●	●
Elixir	M2Y2G64CB8HA9N-DG(XMP)	DDR3 1600	2GB	DS	N/A	Heat-Sink Package	(1333-8-8-8-24)	N/A	●	●	●
Patriot	PVT36G1600LLK(XMP)	DDR3 1600	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	8-8-8-24(1067-7-7-7-20)	1.65	●		

- 6 Dimm :
- **A\***: Supports [two \(2\) modules](#) inserted into slot A1 and B1 as one pair of Dual-channel memory configuration
  - **B\***: Supports [three \(3\) modules](#) inserted into the orange slots (A1, B1 and C1) as one set of Triple-channel memory configuration
  - **C\***: Supports [four \(4\) modules](#) inserted into the orange slots (A1, B1 and C1) and the black slot A2 as one set of Triple-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.  
-It is recommended to install the memory modules from the orange slots for better overclocking capability.  
-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

P6T DELUXE V2 Memory Qualified Vendors List (QVL)

P6T DELUXE V2 DDR3 1800 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Lable(Bios)	Voltage	MM socket support (Optional)		
KINGSTON	KHX1800C9D3T1K3/6GX(XMP)	DDR3 1800	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	(1333-9-9-9-24)	1.65	●	●	●

- 6 Dimm :
- **A\***: Supports [two \(2\) modules](#) inserted into slot A1 and B1 as one pair of Dual-channel memory configuration
  - **B\***: Supports [three \(3\) modules](#) inserted into the orange slots (A1, B1 and C1) as one set of Triple-channel memory configuration
  - **C\***: Supports [four \(4\) modules](#) inserted into the orange slots (A1, B1 and C1) and the black slot A2 as one set of Triple-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.  
-It is recommended to install the memory modules from the orange slots for better overclocking capability.  
-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

P6T DELUXE V2 Memory Qualified Vendors List (QVL)

P6T DELUXE V2 DDR3 1866 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Lable(Bios)	Voltage	MM socket support (Optional)		
G.SKILL	F3-15000CL9D-4GBTD(XMP)	DDR3 1866	4GB(2 x 2GB)	DS	N/A	Heat-Sink Package	9-9-9-24 (1333-9-9-9-24)	1.65	●	●	
KINGSTON	KHX1866C9D3T1K3/6GX(XMP)	DDR3 1866	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	9(1333-9-9-9-24)	1.65	●	●	●
OCZ	OCZ3RPR1866C9LV3GK	DDR3 1866	3GB(3 x 1GB)	SS	N/A	Heat-Sink Package	9-9-9(1066-7-7-7-20)	1.65	●	●	●

- 6 Dimm :
- **A\***: Supports [two \(2\) modules](#) inserted into slot A1 and B1 as one pair of Dual-channel memory configuration
  - **B\***: Supports [three \(3\) modules](#) inserted into the orange slots (A1, B1 and C1) as one set of Triple-channel memory configuration
  - **C\***: Supports [four \(4\) modules](#) inserted into the orange slots (A1, B1 and C1) and the black slot A2 as one set of Triple-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.  
-It is recommended to install the memory modules from the orange slots for better overclocking capability.  
-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.

P6T DELUXE V2 Memory Qualified Vendors List (QVL)

P6T DELUXE V2 DDR3 2000 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Lable(Bios)	Voltage	MM socket support (Optional)		
G.SKILL	F3-16000CL9D-4GBTD(XMP)	DDR3 2000	4GB(2 x 2GB)	DS	N/A	Heat-Sink Package	9-9-9-24 (1333-9-9-9-24)	1.65	●	●	
GEIL	GU34GB2000C9DC(XMP)	DDR3 2000	4GB(2 x 2GB)	DS	N/A	Heat-Sink Package	9-9-9-28 (1333-7-7-7-24)	2	●	●	
KINGSTON	KHX2000C9D3T1K3/3GX(XMP)	DDR3 2000	3GB(3 x 1GB)	SS	N/A	Heat-Sink Package	9 (1333-8-8-8-24)	1.65	●	●	●
KINGSTON	KHX2000C8D3T1K3/3GX(XMP)	DDR3 2000	3GB(3x1GB)	SS	N/A	Heat-Sink Package	8(1333-9-9-9-24)	1.65	●	●	●
KINGSTON	KHX2000C9D3T1K3/6GX(XMP)	DDR3 2000	6GB(3 x 2GB)	DS	N/A	Heat-Sink Package	9 (1333-9-9-9-24)	1.65	●	●	●
KINGSTON	KHX2000C8D3T1K3/6GX(XMP)	DDR3 2000	6GB(3x2GB)	DDR3 2000	N/A	Heat-Sink Package	8(1333-9-9-9-21)	1.65	●	●	●

- 6 Dimm :
- **A\***: Supports [two \(2\) modules](#) inserted into slot A1 and B1 as one pair of Dual-channel memory configuration
  - **B\***: Supports [three \(3\) modules](#) inserted into the orange slots (A1, B1 and C1) as one set of Triple-channel memory configuration
  - **C\***: Supports [four \(4\) modules](#) inserted into the orange slots (A1, B1 and C1) and the black slot A2 as one set of Triple-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.  
-It is recommended to install the memory modules from the orange slots for better overclocking capability.  
-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.