

## P5G41T-M LX2/BR Memory Qualified Vendors List (QVL)

### P5G41T-M LX2/BR DDR3 1067 Qualified Vendors List (QVL)

Vendor	Part No.	Type	Size	SS/DS	Chip Brand	Chip NO.	Timing Lable(Bios)	Voltage	DIMM socket support (Optional)					
									A*	B*	C*	D*	E*	F*
Crucial	CT12864BA1067.8FF	DDR3 1067	1024MB	SS	Micron	9GF22D9KPT	7		●	●				
Crucial	CT25664BA1067.16FF	DDR3 1067	2048MB	DS	Micron	9HF22D9KPT	7		●	●				
Elpida	EBJ51UD8BAFA-AC-E	DDR3 1067	512MB	SS	Elpida	J5308BASE-AC-E			●	●				
Elpida	EBJ51UD8BAFA-AE-E	DDR3 1067	512MB	SS	Elpida	J5308BASE-AC-E			●	●				
Elpida	EBJ11UD8BAFA-AE-E	DDR3 1067	1024MB	DS	Elpida	J5308BASE-AC-E			●	●				
Kingston	KVR1066D3N7/1G	DDR3 1067	1024MB	SS	Kingston	D1288JEKAPGA7U	7	1.5V	●	●				
Kingston	KVR1066D3N7/2G	DDR3 1067	2048MB	DS	Kingston	D1288JEKAPGA7U	7	1.5V	●	●				
Micron	MT8JTF12864AY-1G1D1	DDR3 1067	1024MB	SS	Micron	8ED22D9JNL			●	●				
Micron	MT8JTF12864AZ-1G1F1	DDR3 1067	1024MB	SS	Micron	9GF22D9KPT	7		●	●				
Micron	MT16JTF25664AY-1G1D1	DDR3 1067	2048MB	DS	Micron	8LD22D9JNL			●	●				
Micron	MT16JTF25664AZ-1G1F1	DDR3 1067	2048MB	DS	Micron	9HF22D9KPT	7		●	●				
OCZ	OCZ3SOE10662GK	DDR3 1067	2048MB(Kit of 2)	DS	N/A	Heat-Sink Package	7-7-7-16	1.75V	●	●				
SAMSUNG	M378B2873EH1-CF8	DDR3 1067	1024MB	SS	Samsung	SEC 901 HCF8 K4B1G0846E			●	●				
SAMSUNG	M378B5273BH1-CF8	DDR3 1067	4096MB	DS	SAMSUNG	846 K4B2G0846B-HCF8			●	●				
Elixir	M2Y2G64CBHA9N-BE	DDR3 1067	2048MB	DS	N/A	Heat-Sink Package	7-7-7-20		●	●				
Kingtiger	2GB DIMM PC3-8500	DDR3 1067	2048MB	DS	Hynix	H5TQ1G83AFP G7C			●	●				
<b>Vendor</b>	<b>PartNum.</b>	<b>DDRTYPE</b>	<b>Size</b>	<b>SS/DS</b>	<b>Chip Brand</b>	<b>ChipNum.</b>	<b>Timing - Dimm(Bios)</b>	<b>Vol.</b>						

4 Dimm :

- **A\***: Supports [one module](#) inserted in any slot as Single-channel memory configuration
- **B\***: Supports [2 modules](#) inserted into both the blue or black slots as two pairs of Dual-channel memory configuration

-When installing total memory of 4GB capacity or more, Windows 32-bit operation system may only recognize less than 3GB. Hence, a total installed memory of less than 3GB is recommended.

-It is recommended to install the memory modules from the slots for better overclocking capability.

-The default DIMM frequency depends on its Serial Presence Detect (SPD), which is the standard way of accessing information from a memory module. Under the default state, some memory modules for overclocking may operate at a lower frequency than the vendor-marked value.