

- Additional features and improvements:

1. ROM upgrade to Windows Mobile 6.1.
2. Upgrade the radio FW to V4.6.8-P1 which improve the sound quality and call stability.
3. Bluetooth disconnection problem was fixed (with BT hotfix 3.0 built-in).
4. Solved the bug that can't make video call successfully with SE K850i .
5. Improved the Video call performance and stability
6. The pre-built patch P750\_V6\_2\_0\_SP.zip can enhance system stability, the patch has no need to be installed independently any more.

- Caution:

1. Do not interrupt the upgrade process and avoid touching keypad and screen when upgrading.
2. Please make sure to use SD card with capacity of 2G or less for upgrade. It is recommended to format SD card into FAT format.
3. Please make sure battery level is above 60%.
4. Please make sure that there is no other folder named "2577". If such folder exists, please rename it before the upgrade process.

- Please follow below procedures to upgrade:

1. Please restart your P750 and turn off all wireless connections from start/setting/connection/wireless manager.
2. Plug in power adapter.
3. Unzip and copy all the files and folders (2577, AsusP750.cap, GPSFirmwareUpdate, PegasusP.cap, RadioFirmwareUpdate) into the root directory of a Micro-SD card (Non-SDHC).
4. Insert the Micro SD card to the device and wait for the Autorun.exe to run (It might takes few seconds). If the Autorun.exe does not run automatically, please launch it from \Storage Card\2577\.
5. Follow the instructions until the updating is finished. The whole upgrade process should take about ten minutes.
6. Please Confirm version in "Start"=>"Setting"=>"System"=>"System Information"=>"Version".