Section 1 - Prerequisites

Where and how to run the tool?

1. Auto Install

-Prepare one Micro SD memory card.

-Create folder “2577” in the root of the Micro SD memory card.

-Copy all associated files to the folder “2577”of the Micro SD memory card:

* autorun.exe

*RADIO_FW.dll

*version.txt

-Insert the Micro SD memory card to the slot of device.

-Follow the instructions in Section 2 to complete the update.

Section 2 – Instructions to conduct updating

1	**Please close unnecessary programs first.** Hint：[Start]→[Settings]→[System]→ task manager.	
2	**Make sure the associated files are present in the same directory of the Micro SD memory card.** It includes: *autorun.exe *RADIO_FW.dll *version.txt If you want to use "**Auto Install**" , you have to put these three files in the folder "2577" of the Micro SD card.	
3	**Make sure AC adaptor or USB cable is plugged.**	

	Low power may cause the tool abnormal! If the tool detects that neither AC adaptor nor USB cable is plugged, it will remind user, as the screenshot shows. This tool will be ceased after you tap “ok”. You have to connect AC adaptor or USB and re-start the tool.	
4	**Tap autorun.exe.** If you use “**Auto Install**”, please insert your Micro SD card. The screenshot shows that it begs your confirmation to update modem firmware to V4.6.8-P2?	

	Some notices for you to attend. Tap ok to continue.	
	The screenshot shows that the version of update tool is V4.0.12 For Product. Note: This version is not necessarily the same as the version of the modem firmware.	

5	**The program will run automatically.** **PS: Do not remove AC adaptor and USB cable while updating is in progress.** The screenshot shows the update is in progress (1st stage). The screenshot shows the update is in progress (2nd stage). There will be 2 stages for the update, and it will take about seven minutes.	

6	**Update finished.** The screenshot shows that the device is to reboot. Tap ok to reboot.	