

Component Parts List

Refer to this chapter for a detailed list of the component part numbers and drawings of the ASUS L7000 Series Notebook.

This chapter lists the detailed part number list of the notebook's main system and modules. Please refer to this section when you need to find out specific part numbers for your service needs. You will need to refer to this number when ordering replacement and/or spare parts from ASUS.

This chapter contains the following information:

- System Assembly
- CPU Module
- Case & Module Assembly
- DIMM Cover Assembly
- Heat Sink Plate Assembly
- Modem Module
- Bottom Case Module
- Top Case Module
- Battery Module
- CD-ROM Module
- HDD Module
- LCD Module

SYSTEM
ASSEMBLY

System Assembly

		L7300 System Assembly		
Serial no.	Part no.	Item Name	Total	Remark
-	75-N20AS****	Case & Module Assembly	1	13.3" LCD w/o Modem Cable 13.3" LCD w/ Modem Cable 12.1" LCD w/o Modem Cable 12.1" LCD w/ Modem Cable
F1	70-N20LC****	LCD Module	1	ADI 12.1" 5.5mm Samsung 13.3" 6.8mm
F2	70-N20BT****	Battery Module	1	MORI Li-Ion Panasonic Ni-MH
F3	70-N20CD1100	CD-ROM Module	1	TEAC 24x
F4	70-N20HD****	HDD Module	1	Fujitsu 2.1GB IBM 3.2GB IBM 4GB IBM 6.4GB Hitachi 3.2GB
F5	70-N20MO****	CPU Module	1	Pentium w/ MMX-233 Pentium w/ MMX-266 Pentium II-233 Pentium II-266 Pentium II-300
F6	04-*****	Keyboard	1	Various Language Layouts
-	70-N20FX****	Fax Modem Module	1	Rockwell 56K PC-Tel 56K

CPU MODULE

CPU Module

70-N20MO2100		CPU Module (266)		
Serial no.	Part no.	Item name	Total	Remark
F5-1	01-015226650	CPU P-266	1	Intel Pentium w/ MMX MMC-1/MPPM5PP266
F5-2	13-041206110	Screw M2x6L(B)B-Ni	2	CPU to Heat Sink
F5-3	13-MASXC040B	Screw M2x4L(K)B-Ni	3	CPU to M/B

70-N20MO3100		CPU Module (PII 233)		
Serial no.	Part no.	Item name	Total	Remark
F5-1	01-015523351	CPU PII-233	1	Intel Pentium II/MMC-1 MPPM5P2A233B
F5-2	13-041206110	Screw M2x6L(B)B-Ni	2	CPU to Heat Sink
F5-3	13-MASXC040B	Screw M2x4L(K)B-Ni	3	CPU to M/B

70-N20MO4100		CPU Module (PII 266)		
Serial no.	Part no.	Item name	Total	Remark
F5-1	01-015526651	CPU PII-266	1	Intel Pentium II/MMC-1 MPPM5P2A266B
F5-2	13-041206110	Screw M2x6L(B)B-Ni	2	CPU to Heat Sink
F5-3	13-MASXC040B	Screw M2x4L(K)B-Ni	3	CPU to M/B

70-N20MO5100		CPU Module (PII 300)		
Serial no.	Part no.	Item name	Total	Remark
F5-1	01-015530051	CPU PII-300	1	Intel Pentium II/MMC-1 MPPM5P2A300B
F5-2	13-041206110	Screw M2x6L(B)W-Ni	2	CPU to Heat Sink
F5-3	13-MASXC040B	Screw M2x4L(K)B-Ni	3	CPU to M/B

CASE &
MODULE
ASSEMBLY

Case & Module Assembly

75-N20AS1100		Case & Module Assembly (13.3" LCD) w/o Modem Cable		
Serial no.	Part no.	Item name	Total	Remark
CM1	13-L700AM021	Heat Sink Plate Assembly	1	
CM2	13-L700AM010	DIMM Cover Assembly	1	
CM3	13-L7000M210	Spacer (Fax Modem Board) H=8.0mm	1	
CM4	13-L7000M220	Spacer (IMM) H=4.0mm	3	
CM5	13-L7000P030	Battery Holder Cover	1	
CM6	13-L7000P140	Hinge Cover	2	
CM7	13-L7000P150	LCD Cable Cover	1	
CM10	60-N20CH1400	Charge Board	1	
CM11	70-N20BC1100	Bottom Case Module	1	
CM12	70-N20BX3100	Motherboard Module for 13.3" w/o Modem Conn.	1	
CM13	70-N20TC1100	Top Case Module	1	
CM14	13-MABXC180B	Screw M2x18L(B)B-Ni	9	Heat Sink x 4 Top Case x 1 Top to Base x 4
CM17	13-L7000M271	Bracket for PCMCIA	1	
	13-041205120	Screw M2x5L(B)W-Ni	6	
	13-041308111	Screw M2.5x8L(B)B-Ni, NY	2	
	13-041206110	Screw M2x6L(B)B-Ni	1	
	13-L7000C010	Touch Pad PCMCIA Gasket	1	
	13-L7000C020	Aluminum Foil for I/O Bracket and HDD Guide Bracket	1	
	13-L7000C130	PCMCIA Shielding Foil	1	
	13-L7000L291	Rubber (Modem)	1	
	13-L7000L300	Rubber (I/O Port)	1	
	13-L7000L410	Battery Mylar	1	
	13-L7000L420	Battery Cover Sponge	1	
	13-L7000L470	Keyboard Spacer Sponge	1	
	13-L7000L480	Keyboard Mylar	1	
	13-MAPXD050B	Screw M2.5x5L(P)B-Ni, NY	2	

TECHNICAL SPECIFICATIONS

	13-MASXC040B	Screw M2x4L(K)B-Ni	10	
	15-135007020	BIOS Label for P/II & Advanced ACPI	1	

75-N20AS1110		Case & Module Assembly (13.3" LCD) W/ Modem Cable		
Serial no.	Part no.	Item name	Total	Remark
CM1	13-L700AM021	Heat Sink Plate Assembly	1	
CM2	13-L700AM010	DIMM Cover Assembly	1	
CM3	13-L7000M210	Spacer (Fax Modem Board) H=8.0mm	1	
CM4	13-L7000M220	Spacer (IMM) H=4.0mm	3	
CM5	13-L7000P030	Battery Holder Cover	1	
CM6	13-L7000P140	Hinge Cover	2	
CM7	13-L7000P150	LCD Cable Cover	1	
CM10	60-N20CH1400	Charge Board	1	
CM11	70-N20BC1100	Bottom Case Module	1	
CM12	70-N20BX1100	Motherboard Module for 13.3" w/ Modem Conn.	1	
CM13	70-N20TC1100	Top Case Module	1	
CM14	13-MABXC180B	Screw M2x18L(B)B-Ni	9	Heat Sink x 4 Top Case x 1 Top to Base x 4
CM17	13-L7000M271	Bracket for PCMCIA	1	
	13-041205120	Screw M2x5L(B)W-Ni	6	
	13-041308111	Screw M2.5x8L(B)B-Ni, NY	2	
	13-041206110	Screw M2x6L(B)B-Ni	1	
	13-L7000C010	Touch Pad PCMCIA Gasket	1	
	13-L7000C020	Aluminum Foil for I/O Bracket and HDD Guide Bracket	1	
	13-L7000C130	PCMCIA Shielding Foil	1	
	13-L7000L291	Rubber (Modem)	1	
	13-L7000L300	Rubber (I/O Port)	1	
	13-L7000L410	Battery Mylar	1	
	13-L7000L420	Battery Cover Sponge	1	
	13-L7000L470	Keyboard Spacer Sponge	1	
	13-L7000L480	Keyboard Mylar	1	

TECHNICAL SPECIFICATIONS

	13-MAPXD050B	Screw M2.5x5L(P)B-Ni,NY	2	
	13-MASXC040B	Screw M2x4L(K)B-Ni	10	
	15-135007020	BIOS Label for P/II & Advanced ACPI	1	
	14-140310020	Wire Cable 2P (Modem) L=100mm	1	

75-N20AS2100		Case & Module Assembly (12.1" LCD) w/o Modem Cable		
Serial no.	Part no.	Item name	Total	Remark
CM1	13-L700AM021	Heat Sink Plate Assembly	1	
CM2	13-L700AM010	DIMM Cover Assembly	1	
CM3	13-L7000M210	Spacer (Fax Modem Board) H=8.0mm	1	
CM4	13-L7000M220	Spacer (IMM) H=4.0mm	3	
CM5	13-L7000P030	Battery Holder Cover	1	
CM6	13-L7000P140	Hinge Cover	2	
CM7	13-L7000P150	LCD Cable Cover	1	
CM10	60-N20CH1400	Charge Board	1	
CM11	70-N20BC1100	Bottom Case Module	1	
CM12	70-N20BX4100	Motherboard Module for 12.1" w/o Modem Conn.	1	
CM13	70-N20TC1100	Top Case Module	1	
CM14	13-MABXC180B	Screw M2x18L(B)B-Ni	9	Heat Sink x 4 Top Case x 1 Top to Base x 4
CM17	13-L7000M271	Bracket for PCMCIA	1	
	13-041205120	Screw M2x5L(B)W-Ni	6	
	13-041308111	Screw M2.5x8L(B)B-Ni, NY	2	
	13-041206110	Screw M2x6L(B)B-Ni	1	
	13-L7000C010	Touch Pad PCMCIA Gasket	1	
	13-L7000C020	Aluminum Foil for I/O Bracket and HDD Guide Bracket	1	
	13-L7000C130	PCMCIA Shielding Foil	1	
	13-L7000L291	Rubber (Modem)	1	
	13-L7000L300	Rubber (I/O Port)	1	
	13-L7000L410	Battery Mylar	1	

TECHNICAL SPECIFICATIONS

	13-L7000L420	Battery Cover Sponge	1	
	13-L7000L470	Keyboard Spacer Sponge	1	
	13-L7000L480	Keyboard Mylar	1	
	13-MAPXD050B	Screw M2.5x5L(P)B-Ni,NY	2	
	13-MASXC040B	Screw M2x4L(K)B-Ni	10	
	15-135007020	BIOS Label for P/II & Advanced ACPI	1	

75-N20AS2110		Case & Module Assembly (12.1" LCD) w/ Modem Cable		
Serial no.	Part no.	Item name	Total	Remark
CM1	13-L700AM021	Heat Sink Plate Assembly	1	
CM2	13-L700AM010	DIMM Cover Assembly	1	
CM3	13-L7000M210	Spacer (Fax Modem Board) H=8.0mm	1	
CM4	13-L7000M220	Spacer (IMM) H=4.0mm	3	
CM5	13-L7000P030	Battery Holder Cover	1	
CM6	13-L7000P140	Hinge Cover	2	
CM7	13-L7000P150	LCD Cable Cover	1	
CM10	60-N20CH1400	Charge Board	1	
CM11	70-N20BC1100	Bottom Case Module	1	
CM12	70-N20BX2100	Motherboard Module for 12.1" w/ Modem Conn.	1	
CM13	70-N20TC1100	Top Case Module	1	
CM14	13-MABXC180B	Screw M2x18L(B)B-Ni	9	Heat Sink x 4 Top Case x 1 Top to Base x 4
CM17	13-L7000M271	Bracket for PCMCIA	1	
	13-041205120	Screw M2x5L(B)W-Ni	6	
	13-041308111	Screw M2.5x8L(B)B-Ni, NY	2	
	13-041206110	Screw M2x6L(B)B-Ni	1	
	13-L7000C010	Touch Pad PCMCIA Gasket	1	
	13-L7000C020	Aluminum Foil for I/O Bracket and HDD Guide Bracket	1	
	13-L7000C130	PCMCIA Shielding Foil	1	
	13-L7000L291	Rubber (Modem)	1	

TECHNICAL SPECIFICATIONS

	13-L7000L300	Rubber (I/O Port)	1	
	13-L7000L410	Battery Mylar	1	
	13-L7000L420	Battery Cover Sponge	1	
	13-L7000L470	Keyboard Spacer Sponge	1	
	13-L7000L480	Keyboard Mylar	1	
	13-MAPXD050B	Screw M2.5x5L(P)B-Ni,NY	2	
	13-MASXC040B	Screw M2x4L(K)B-Ni	10	
	15-135007020	BIOS Label for P/II & Advanced ACPI	1	
	14-140310020	Wire Cable 2P (Modem) L=100mm	1	

 DIMM COVER
ASSEMBLY

DIMM Cover Assembly

60-L700AM010		DIMM Cover Assembly		
Serial no.	Part no.	Item name	Total	Remark
	13-L7000C070	Gasket DIMM (up)	1	
	13-L7000C080	Gasket DIMM (down)	2	
	13-L7000L140	DIMM Cover Mylar	1	
	13-L7000L200	DIMM Cover CR (Inner)	1	
	13-L7000M140	DIMM Cover	1	

 HEAT SINK
PLATE
ASSEMBLY

Heat Sink Plate Assembly


60-L700AM021		Heat Sink Plate Assembly		
Serial no.	Part no.	Item name	Total	Remark
	13-L7000C050	Thermal Pad (CPU)	1	
	13-L7000M011	Heat Sink Plate	1	Aluminum
	13-L7000M300	Heat Sink Block w/ Heat Pipe	1	
	13-MAKXC040B	Screw M2x4L(K)B-Ni	2	Thermal pad x 2

 MODEM
MODULE

Modem Module

70-N20FX1100		Modem Module		
Serial no.	Part no.	Item name	Total	Remark
	13-MAKXC040B	Screw M2x4L(K)B-Ni	1	Modem to M/B x 1
		Fax Modem Rockwell	1	V.90 56K

TECHNICAL SPECIFICATIONS



B O T T O M
C A S E M O D U L E

Bottom Case Module


70-N20BC1100		Bottom Case Module		
Serial no.	Part no.	Item name	Total	Remark
BC1	04-170000410	Speaker Set	1	
BC2	13-F7000L430	Rubber Foot (Rare)	4	Grey
BC3	13-F7000M340	PCMCIA Door Spring	1	
BC4	13-F7001P340	PCMCIA Door (L)	1	
BC5	13-F7001P350	Raising Foot (L)	1	
BC6	13-F7001P360	Raising Foot (R)	1	
BC7	13-L7000P180	Power Knob	1	Silver
BC8	13-L7000P190	IR-Lens	1	Purple
BC9	13-L700AP032	Bottom Case Sub-Assembly	1	
	13-L7000C030	Gasket I/O (L)	1	
	13-L7000C040	Gasket I/O (R)	1	
	13-L7000L360	Spacer Mylar for Bottom Case	1	
	13-L7000L380	Holder Mylar for Bottom Case	1	

B O T T O M
C A S E S U B -
A S S E M B L Y

Bottom Case Sub-Assembly

13-L700AP032		Bottom Case Sub-Assembly		
Serial no.	Part no.	Item name	Total	Remark
	13-L7000C090	CD-ROM Shielding Foil	1	
	13-L7000C100	Bottom Bracket Foil (L)	1	
	13-L7000C110	Bottom Bracket Foil (R)	1	
	13-L7000C210	Bottom Bracket Mylar	1	
	13-L7000M071	Bottom Bracket	1	
	13-L7000P120	Bottom Case	1	

TECHNICAL SPECIFICATIONS



TOP CASE
MODULE

Top Case Module


70-N20TC1100		Top Case Module		
Serial no.	Part no.	Item name	Total	Remark
TC1	04-110100020	TouchPad	1	ALPS KGDDFQ951A
TC2	13-041203210	Screw M2x3L(K)B-Ni	8	TouchPad x 4 SW/PCB x 2 FDD x 2
TC3	13-041303220	Screw M2.5x3L(K)W-Ni	4	FDD Side x 4
TC4	13-F7000M340	PCMCIA Door Spring	1	
TC5	13-F7001P330	PCMCIA Door (U)	1	
TC6	13-L7000L130	TouchPad Mylar	1	
TC7	13-L7000M100	FDD Bracket	1	
TC8	13-L7000M130	TouchPad Bracket	1	
TC9	14-140314151	Wire Cable 15P L=160mm (TouchPad/Switch Board)	1	
TC10	14-140328202	Wire Cable 2P L=50mm (Lid Switch Cable)	1	
TC11	17-021225002	FDD 1.44MB 3.5" High	1	Citizen W1DE-63BE
TC12	60-N20SW1200	Switch Board	1	
TC13	08-260000400	FDD FPC	1	
TC14	08-260000510	TouchPad FPC	1	
TC15	13-L700AP041	Top Case Sub-Assembly	1	
TC16	13-MAKXA040W	Screw M1.4x4L(K)W-Ni	1	Lid Switch x 1
	13-L7000L250	Switch Board Mylar	1	
	13-L7000L370	Sponge-A for Top Case	1	
	13-L7000L450	FDD Bracket Mylar	1	
	13-L7000L490	Switch Board/PCB Mylar	1	

Top Case Sub-Assembly

TOP CASE
SUB-
ASSEMBLY

60-L700AP041		Top Case Sub-Assembly		
Serial no.	Part no.	Item name	Total	Remark
	13-L7000M191	Keyboard Lock Spring	2	
	13-L7000M200	Keyboard Lock Cover	2	
	13-L7000P111	Top Case	1	
	13-L7000P170	TouchPad Knob	1	
	13-L7000P200	LED Lens	1	
	13-L7000P210	Keyboard Lock Knob	2	

TECHNICAL SPECIFICATIONS



BATTERY
MODULE

Battery Module

70-N20BT1100		Battery Module (Li-Ion)		
Serial no.	Part no.	Item name	Total	Remark
BT1	07-016501865	Battery Li-Ion	1	MORI CGR 18650 x 9
BT3	13-L7000P010	Battery Top Cover	1	
BT4	13-L7000P020	Battery Bottom Cover	1	
BT5	60-N10GB1400	Gauge Board (Li)	1	
	15-100302700	Li-Ion Battery Pack Label (ASUS)	1	Top "ASUS"
	15-100302900	Battery Pack Bottom Label (ASUS)		Bottom "ASUS"


70-N20BT1110		Battery Module (Li-Ion)		
Serial no.	Part no.	Item name	Total	Remark
BT1	07-016100100	Battery Li-Ion	1	Panasonic CGR 18650 x 9
BT3	13-L7000P010	Battery Top Cover	1	
BT4	13-L7000P020	Battery Bottom Cover	1	
BT5	60-N10GB1400	Gauge Board (Li)	1	
	15-100302710	Li-Ion Battery Pack Label (Generic)	1	Top "Generic"
	15-100302900	Battery Pack Bottom Label (Generic)		Bottom "Generic"

70-N20BT2100		Battery Module (Ni-MH)		
Serial no.	Part no.	Item name	Total	Remark
BT1	07-017100010	Battery Ni-MH	1	Toshiba 4000mAh 9S +10.8V
BT3	13-L7000P010	Battery Top Cover	1	
BT4	13-L7000P020	Battery Bottom Cover	1	
BT5	60-N10GB2100	Gauge Board (Ni-MH)	1	
	15-100302800	Ni-MH Battery Pack Label (ASUS)	1	Top "ASUS"
	15-100302900	Battery Pack Bottom Label (ASUS)		Bottom "ASUS"

TECHNICAL SPECIFICATIONS

70-N20BT2110		Battery Module (Ni-MH)		
Serial no.	Part no.	Item name	Total	Remark
BT1	07-017100010	Battery Ni-MH	1	Toshiba 4000mAh 9S +10.8V
BT3	13-L7000P010	Battery Top Cover	1	
BT4	13-L7000P020	Battery Bottom Cover	1	
BT5	60-N10GB2100	Gauge Board (Ni-MH)	1	
	15-100302810	Ni-MH Battery Pack Label (Generic)	1	Top "Generic"
	15-100302910	Battery Pack Bottom Label (Generic)		Bottom "Generic"

TECHNICAL SPECIFICATIONS



CD-ROM
MODULE

CD-ROM Module


70-N20CD1100		CD-ROM Module		
Serial no.	Part no.	Item name	Total	Remark
CR1	08-260000220	CD-ROM FPC	1	
CR2	13-L7000M080	CD-ROM Bracket (R)	1	
CR3	13-L7000M090	CD-ROM Bracket (L)	1	
CR4	13-MAPXC020W	Screw M2x2L(P)W-Ni	4	CD Side x 4
CR5	13-030717241	IDE CD-ROM	1	TEAC 24X/ CD-224E-A92
CR6	13-L700AP020	CD-ROM Bezel Assembly	1	
CR7	13-MCKXC050B	Screw M2x5L(K)B-Ni	3	Front Panel x 3
	13-L7000L280	CD-ROM Isolate Mylar	1	

CD-ROM
BEZEL
ASSEMBLY

CD-ROM Bezel Assembly

13-L700AP040		CD-ROM Bezel Assembly		
Serial no.	Part no.	Item name	Total	Remark
	13-L7000P240	CD-ROM Lens	1	
	13-L7001P440	CD-ROM Knob	1	
	13-L7000P130	CD-ROM Bezel	1	

TECHNICAL SPECIFICATIONS



HDD MODULE

HDD Module

70-N20HD4100		HDD Module (IBM 6.4GB)		
Serial no.	Part no.	Item name	Total	Remark
H1	12-161510441	HDD Connector 44P, 2.0mm	1	
H2	13-041404220	Screw M3x4L(K)W-Ni	4	Side x 4
H3	13-F7000M291	HDD Shielding Plate	1	
H4	13-F7000M270	Fix Screw for HDD Fe- Ni, L=5mm	1	Fix Screw x 1
H5	13-L7000L081	HDD Mylar	1	
H6	13-L7000P160	HDD Case	1	
H7	17-013114700	IDE HDD 6.4GB	1	IBM 6.4GB/ DADA-26480

70-N20HD3100		HDD Module (Fujitsu 2.1GB)		
Serial no.	Part no.	Item name	Total	Remark
H1	12-161510441	HDD Connector 44P, 2.0mm	1	
H2	13-041404220	Screw M3x4L(K)W-Ni	4	Side x 4
H3	13-F7000M291	HDD Shielding Plate	1	
H4	13-F7000M270	Fix Screw for HDD Fe- Ni, L=5mm	1	Fix Screw x 1
H5	13-L7000L081	HDD Mylar	1	
H6	13-L7000P160	HDD Case	1	
H7	17-013108110	IDE HDD 2.1GB	1	Fujitsu 2.1GB/ MHD2021AT

70-N20HD2110		HDD Module (IBM 4GB)		
Serial no.	Part no.	Item name	Total	Remark
H1	12-161510441	HDD Connector 44P, 2.0mm	1	
H2	13-041404220	Screw M3x4L(K)W-Ni	4	Side x 4
H3	13-F7000M291	HDD Shielding Plate	1	
H4	13-F7000M270	Fix Screw for HDD Fe- Ni, L=5mm	1	Fix Screw x 1
H5	13-L7000L081	HDD Mylar	1	
H6	13-L7000P160	HDD Case	1	
H7	17-013112120	IDE HDD 4.3GB	1	IBM 4.3GB/ DTCA-24090


TECHNICAL SPECIFICATIONS

70-N20HD1110		HDD Module (IBM 3.2GB)		
Serial no.	Part no.	Item name	Total	Remark
H1	12-161510441	HDD Connector 44P, 2.0mm	1	
H2	13-041404220	Screw M3x4L(K)W-Ni	4	Side x 4
H3	13-F7000M291	HDD Shielding Plate	1	
H4	13-F7000M270	Fix Screw for HDD Fe- Ni, L=5mm	1	Fix Screw x 1
H5	13-L7000L081	HDD Mylar	1	
H6	13-L7000P160	HDD Case	1	
H7	17-013110700	IDE HDD 3.2GB	1	IBM 3.2GB/ DKLA-23240

70-N20HD1100		HDD Module (Hitachi 3.2GB)		
Serial no.	Part no.	Item name	Total	Remark
H1	12-161510441	HDD Connector 44P, 2.0mm	1	
H2	13-041404220	Screw M3x4L(K)W-Ni	4	Side x 4
H3	13-F7000M291	HDD Shielding Plate	1	
H4	13-F7000M270	Fix Screw for HDD Fe-Ni, L=5mm	1	Fix Screw x 1
H5	13-L7000L081	HDD Mylar	1	
H6	13-L7000P160	HDD Case	1	
H7	17-013110900	IDE HDD 3.2GB	1	Hitachi 3.2GB/ DK226A-32U

70-N20HD0100		HDD Housing Module		
Serial no.	Part no.	Item name	Total	Remark
H1	12-161510441	HDD Connector 44P, 2.0mm	1	
H2	13-041404220	Screw M3x4L(K)W-Ni	4	Side x 4
H3	13-F7000M291	HDD Shielding Plate	1	
H4	13-F7000M270	Fix Screw for HDD Fe-Ni, L=5mm	1	Fix Screw x 1
H5	13-L7000L081	HDD Mylar	1	
H6	13-L7000P160	HDD Case	1	

TECHNICAL SPECIFICATIONS



LCD MODULE

LCD Module

70-N20LC1100		LCD Module (ADI 12.1" 5.5mm)		
Serial no.	Part no.	Item name	Total	Remark
LM1	08-260000310	LCD FPC for ADI 12.1"	1	
LM2	13-MBBXD040B	Screw M2.5x4L(K)B-Ni, NY	4	Bracket to case x 4
LM3	13-MAKXD050W	Screw M2.5x5L(K)W-Ni	2	Hinge to case x 2
LM4	13-MBKXD060W	Screw M2.5x6L(K)W-Ni, NY	3	Case (bottom) x 3
LM5	13-L7000L441	Rubber (LCD Bezel)	2	
LM6	13-L7000L040	LCD Rubber (Hinge)	3	
LM7	13-L7000L051	LCD Screw Pad	4	
LM8	13-L7000M041	Hinge (R)	1	
LM9	13-L7000M051	Hinge (L)	1	
LM10	13-L7000M160	Hook Spring	2	
LM11	13-L7000M251	LCD Bracket (R) (12.1")	1	
LM12	13-L7000M261	LCD Bracket (L) (12.1")	1	
LM13	13-L7000P051	LCD Front Cover (12.1")	1	
LM14	13-L7000P070	LCD Hook (R)	1	
LM15	13-L7000P080	LCD Hook (L)	1	
LM16	13-L7000P090	LCD Hook Knob (R)	1	
LM18	13-MASXC040B	Screw M2x4L(K)B-Ni	4	Case (Side) x 4
LM19	14-100303101	Cable for Inverter, L=80mm	1	
LM20	18-241205100	LCD TFT 12.1"	1	ADI 12.1" / AA121SJ01
LM21	60-N20IN1200	Inverter Board	1	
LM22	13-L7000P100	LCD Hook Knob (L)	1	
LM23	14-140320020	Wire Cable 2P L=200mm	1	
LM24	13-L7000M231	LCD Back Cover (12.1")	1	
	13-L7000C140	Spacer Washer for PCMCIA	1	
	13-L7000L231	Rubber (Microphone)	1	
	13-L7000L260	Inverter Mylar	1	
	13-L7000L310	LCD Bracket Rubber (12.1")	1	
	13-L7000L340	LCD Back Sponge (12.1" ADI)	1	


TECHNICAL SPECIFICATIONS

70-N20LC1110		LCD Module (Samsung 13.3" 6.8mm)		
Serial no.	Part no.	Item name	Total	Remark
	08-260000302	LCD FPC for Samsung 13.3"	1	
	13-041203210	Screw M2x3L(K)B-Ni	4	Hinge x 4
	13-L7000L140	Spacer Washer for PCMCIA	1	
	13-L7000L040	LCD Rubber (Hinge)	3	
	13-L7000L051	LCD Screw Pad	4	
	13-L7000L160	LCD Wire Tape	1	
	13-L7000L170	Hook Area Mylar	2	
	13-L7000L231	Rubber (Microphone)	1	
	13-L7000L260	Inverter Mylar	1	
	13-L7000L320	LCD Back Sponge (13.3")	1	
	13-L7000L330	MICA Sheet (13.3")	1	
	13-L7000L441	Rubber (LCD Bezel)	2	
	13-L7000M021	LCD Bracket (R) (13.3")	1	
	13-L7000M031	LCD Bracket (L) (13.3")	1	
	13-L7000M041	Hinge (R)	1	
	13-L7000M051	Hinge (L)	1	
	13-L7000M160	Hook Spring	2	
	13-L7000P041	LCD Front Cover (13.3")	1	
	13-L7000P061	LCD Back Cover (13.3")	1	
	13-L7000P070	LCD Hook (R)	1	
	13-L7000P080	LCD Hook (L)	1	
	13-L7000P090	LCD Hook Knob (R)	1	
	13-L7000P100	LCD Hook Knob (L)	1	
	13-MASXC040B	Screw M2x4L(K)B-Ni	4	
	13-MBBXD040B	Screw M2.5x4L(B)B-Ni, NY	2	
	13-MBKXD060W	Screw M2.5x6L(K)W-Ni, NY	3	
	14-100303101	Cable for Inverter, L=80mm	1	
	18-241306100	LCD TFT	1	Samsung 13.3" / LT133X5-122
	60-N20IN1200	Inverter Board	1	

TECHNICAL SPECIFICATIONS

70-N20LC1120		LCD Module (Sanyo 12.1")		
Serial no.	Part no.	Item name	Total	Remark
	08-260000322	LCD FPC for Sanyo 12.1"	1	
	13-L7000L140	Spacer Washer for PCMCIA	1	
	13-L7000L040	LCD Rubber (Hinge)	3	
	13-L7000L051	LCD Screw Pad	4	
	13-L7000L231	Rubber (Microphone)	1	
	13-L7000L260	Inverter Mylar	1	
	13-L7000L310	LCD Bracket Rubber (12.1")	1	
	13-L7000L350	LCD Back Sponge (12.1" Sanyo)	1	
	13-L7000L441	Rubber (LCD Bezel)	2	
	13-L7000M041	Hinge (R)	1	
	13-L7000M051	Hinge (L)	1	
	13-L7000M160	Hook Spring	2	
	13-L7000M251	LCD Bracket (R) (12.1")	1	
	13-L7000M261	LCD Bracket (L) (12.1")	1	
	13-L7000P051	LCD Front Cover (12.1")	1	
	13-L7000P070	LCD Hook (R)	1	
	13-L7000P080	LCD Hook (L)	1	
	13-L7000P090	LCD Hook Knob (R)	1	
	13-L7000P100	LCD Hook Knob (L)	1	
	13-L7000P061	LCD Back Cover (12.1")	1	
	13-MAKXD050W	Screw M2.5x5L(K)W-Ni	2	
	13-MASXC040B	Screw M2x4L(K)B-Ni	4	
	13-MBBXD040B	Screw M2.5x4L(B)B-Ni, NY	4	
	13-MBKXD060W	Screw M2.5x6L(K)W-Ni, NY	3	
	14-100303101	Cable for Inverter, L=80mm	1	
	14-140320030	Wire Cable 3P L=200mm	1	
	18-241205200	LCD TFT	1	Sanyo 12.1"/ TM121SV- 02L01A
	60-N20IN1200	Inverter Board	1	

TECHNICAL SPECIFICATIONS



M / B MODULE

Motherboard Module

70-N20BX4100		Motherboard Module (12.1") w/o Fax Modem Connector		
Serial no.	Part no.	Item name	Total	Remark
MB1	13-021019000	Hex Hut 3.5	3	EJW-A-C, for audio jacks x 3
MB2	13-MAFXC040B	Screw M2x4L(F)B-Ni	2	HDD guide x 2
MB3	13-042505001	Screw Hex 5mm	6	I/O port x 6
MB4	13-070300010	Fan	1	SEPA SFB25A-05HA-001B
MB5	13-L7000L090	MPCB Mylar (HDD)	1	
MB6	13-L7000M120	I/O Bracket	1	
MB7	13-L7000M150	HDD Guide Bracket	1	
MB8	13-MAKXC110W	Screw M2x11L(K)W-Ni	2	Fan x 2
MB9	60-N20MB4100	Main Board for 12.1" w/o Modem	1	TTL I/F LCD
	13-L7000C120	PS/2 Gasket	1	
	13-L7000M280	Bracket I/O 2	1	

70-N20BX3100		Motherboard Module (13.3") w/o Fax Modem Connector		
Serial no.	Part no.	Item name	Total	Remark
MB1	13-021019000	Hex Hut 3.5	3	EJW-A-C, for audio jacks x 3
MB2	13-MAFXC040B	Screw M2x4L(F)B-Ni	2	HDD guide x 2
MB3	13-042505001	Screw Hex 5mm	6	I/O port x 6
MB4	13-070300010	Fan	1	SEPA SFB25A-05HA-001B
MB5	13-L7000L090	MPCB Mylar (HDD)	1	
MB6	13-L7000M120	I/O Bracket	1	
MB7	13-L7000M150	HDD Guide Bracket	1	
MB8	13-MAKXC110W	Screw M2x11L(K)W-Ni	2	Fan x 2
MB9	60-N20MB3100	Main Board for 13.3" w/o Modem	1	LVDS I/F LCD
	13-L7000C120	PS/2 Gasket	1	
	13-L7000M280	Bracket I/O 2	1	

TECHNICAL SPECIFICATIONS

70-N20BX2100		Motherboard Module (12.1")		
Serial no.	Part no.	Item name	Total	Remark
MB1	13-021019000	Hex Hut 3.5	3	EJW-A-C, for audio jacks x 3
MB2	13-MAFXC040B	Screw M2x4L(F)B-Ni	2	HDD guide x 2
MB3	13-042505001	Screw Hex 5mm	6	I/O port x 6
MB4	13-070300010	Fan	1	SEPA SFB25A-05HA-001B
MB5	13-L7000L090	MPCB Mylar (HDD)	1	
MB6	13-L7000M120	I/O Bracket	1	
MB7	13-L7000M150	HDD Guide Bracket	1	
MB8	13-MAKXC110W	Screw M2x11L(K)W-Ni	2	Fan x 2
MB9	60-N20MB2200	Main Board for 12.1"	1	TTL I/F LCD
	13-L7000C120	PS/2 Gasket	1	
	13-L7000M280	Bracket I/O 2	1	

70-N20BX1100		Motherboard Module (13.3")		
Serial no.	Part no.	Item name	Total	Remark
MB1	13-021019000	Hex Hut 3.5	3	EJW-A-C, for audio jacks x 3
MB2	13-MAFXC040B	Screw M2x4L(F)B-Ni	2	HDD guide x 2
MB3	13-042505001	Screw Hex 5mm	6	I/O port x 6
MB4	13-070300010	Fan	1	SEPA SFB25A-05HA-001B
MB5	13-L7000L090	MPCB Mylar (HDD)	1	
MB6	13-L7000M120	I/O Bracket	1	
MB7	13-L7000M150	HDD Guide Bracket	1	
MB8	13-MAKXC110W	Screw M2x11L(K)W-Ni	2	Fan x 2
MB9	60-N20MB1200	Main Board for 13.3"	1	LVDS I/F LCD
	13-L7000C120	PS/2 Gasket	1	
	13-L7000M280	Bracket I/O 2	1	


M / B

(C A R D B U S)

Main Board (CardBus)

59-N20MB-CB		Main Board (CardBus)		
Serial no.	Part no.	Item name	Total	Remark
CB1	12-210013600	Card Bus	1	OTAX/SK98037-1
CB3	13-MAKXC140W	Screw M2x14L(K)W-Ni	2	PCMCIA Box x 2

TECHNICAL SPECIFICATIONS



TECHNICAL SPECIFICATIONS

